



Report No.: T190625D08-I-E

Ref. No.: T190111D10-E

Page: 1 / 87  
Rev.: 01

# CE EMC TEST REPORT

for

LCD Touch Control Panel

MODEL: PT2104; KT2104; GT2104; MMPT2104; xPT2104; MT2104; FT2104; FC2104;  
DAK-2104B; LUI2104; MG-T2104-24; SK2104; eV2104; MT2104; TV2104;  
AST-2104THSxx; VT92104T; PY2104-AST; PSST2104-AST; PT2104-AST; KT2104-AST;  
ET2104-AST; ET2104-AST; THM2104A; MZ600-TT2104H; VM12104-AST; VM12104-AS;  
VM12104-AH; RT2104; RL2104; KT2104; PL2104; KL2104; AS43TFT1025; WOP-2100T;  
GPT2104; XI33B-T2B; xPT2104; HT2104; AS46TFT1007; CPT2104; PMT2104; IPT2104;  
IV214M-SEAP; IHM104T2E; IM-PT2104

Issued to:

**Cermate Technologies Inc.**

7F-1, No. 168, Liancheng Rd., Zhonghe Dist.,  
New Taipei City, 23553, TAIWAN, R.O.C.

Issued by:

**Compliance Certification Services Inc.**

**Xindian Lab.**

No.163-1, Jhongsheng Rd., Xindian Dist.,  
New Taipei City, 23151 Taiwan.

TEL: 886-2-22170894

FAX: 886-2-22171029

**Issued Date: August 2, 2019**

**Note:** This document may be altered or revised by Compliance Certification Services Inc. personnel only, and shall be noted in the revision section of the document. The client should not use it to claim product endorsement by TAF, A2LA, NIST or any government agencies.

Unless otherwise stated the results shown in this test report refer only to the sample(s) tested and such sample(s) are retained for 90 days only.

除非另有說明，此報告結果僅對測試之樣品負責，同時此樣品僅保留90天。本報告未經本公司書面許可，不可部分複製。

This document is issued by the Company subject to its General Conditions of Service printed overleaf, available on request or accessible at [www.sgs.com/terms\\_and\\_conditions.htm](http://www.sgs.com/terms_and_conditions.htm) and for electronic format documents, subject to Terms and Conditions for Electronic Documents at [www.sgs.com/terms\\_e-document.htm](http://www.sgs.com/terms_e-document.htm). Attention is drawn to the limitation of liability, indemnification and jurisdiction issues defined therein. Any holder of this document is advised that information contained hereon reflects the Company's findings at the time of its intervention only and within the limits of Client's instructions, if any. The Company's sole responsibility is to its Client and this document does not exonerate parties to a transaction from exercising all their rights and obligations under the transaction documents. This document cannot be reproduced except in full, without prior written approval of the Company. Any unauthorized alteration, forgery or falsification of the content or appearance of this document is unlawful and offenders may be prosecuted to the fullest extent of the law.



**Report No.:** T190625D08-I-E

**Ref. No.:** T190111D10-E

Page: 2 / 87  
Rev.: 01

**Revision History**

Rev.	Issue Date	Revisions	Effect Page	Revised By
00	February 11, 2019	Initial Issue	ALL	Eva Fan
01	August 2, 2019	Add models	ALL	Eva Fan



Report No.: T190625D08-I-E

Ref. No.: T190111D10-E

Page: 3 / 87  
Rev.: 01

## TABLE OF CONTENTS

<b>1</b>	<b>TEST CERTIFICATION .....</b>	<b>4</b>
<b>2</b>	<b>TEST RESULT SUMMARY .....</b>	<b>5</b>
<b>3</b>	<b>EUT DESCRIPTION .....</b>	<b>6</b>
<b>4</b>	<b>TEST METHODOLOGY .....</b>	<b>7</b>
4.1.	DECISION OF FINAL TEST MODE.....	7
4.2.	EUT SYSTEM OPERATION .....	7
<b>5</b>	<b>SETUP OF EQUIPMENT UNDER TEST .....</b>	<b>8</b>
5.1.	DESCRIPTION OF SUPPORT UNITS.....	8
5.2.	CONFIGURATION OF SYSTEM UNDER TEST .....	8
<b>6</b>	<b>FACILITIES AND ACCREDITATIONS .....</b>	<b>9</b>
6.1.	FACILITIES .....	9
6.2.	ACCREDITATIONS .....	9
6.3.	MEASUREMENT UNCERTAINTY .....	9
<b>7</b>	<b>EMISSION TEST .....</b>	<b>10</b>
7.1.	CONDUCTED EMISSION MEASUREMENT .....	10
7.2.	CONDUCTED EMISSION MEASUREMENT AT TELECOMMUNICATION PORTS.....	17
7.3.	RADIATED EMISSION MEASUREMENT.....	21
7.4.	HARMONICS CURRENT MEASUREMENT.....	32
7.5.	VOLTAGE FLUCTUATION AND FLICKER MEASUREMENT .....	37
<b>8</b>	<b>IMMUNITY TEST .....</b>	<b>40</b>
8.1.	GENERAL DESCRIPTION .....	40
8.2.	GENERAL PERFORMANCE CRITERIA DESCRIPTION.....	41
8.3.	ELECTROSTATIC DISCHARGE (ESD) .....	42
8.4.	RADIATED, RADIO-FREQUENCY, ELECTROMAGNETIC FIELD (RS) .....	48
8.5.	ELECTRICAL FAST TRANSIENT (EFT) .....	52
8.6.	SURGE IMMUNITY TEST .....	55
8.7.	CONDUCTED RADIO FREQUENCY DISTURBANCES (CS).....	58
8.8.	POWER FREQUENCY MAGNETIC FIELD .....	61
8.9.	VOLTAGE DIPS & VOLTAGE INTERRUPTIONS .....	64
<b>9</b>	<b>PHOTOGRAPHS OF THE TEST CONFIGURATION.....</b>	<b>66</b>
	<b>APPENDIX 1 - PHOTOGRAPHS OF EUT .....</b>	<b>A1-1</b>

# 1 TEST CERTIFICATION

**Product:** LCD Touch Control Panel

**Model:** PT2104; KT2104; GT2104; MMPT2104; xPT2104; MT2104; FT2104; FC2104; DAK-2104B; LUI2104; MG-T2104-24; SK2104; eV2104; MT2104; TV2104; AST-2104THSxx; VT92104T; PY2104-AST; PSST2104-AST; PT2104-AST; KT2104-AST; ET2104-AST; ET2104-AST; THM2104A; MZ600-TT2104H; VM12104-AST; VM12104-AS; VM12104-AH; RT2104; RL2104; KT2104; PL2104; KL2104; AS43TFT1025; WOP-2100T; GPT2104; XI33B-T2B; xPT2104; HT2104; AS46TFT1007; CPT2104; PMT2104; IPT2104; IV214M-SEAP; IHM104T2E; IM-PT2104

**Brand:** Cermate

**Applicant:** Cermate Technologies Inc.  
7F.-1, No.168, Liancheng Rd., Zhonghe Dist.,  
New Taipei City 23553, Taiwan (R.O.C.)

**Manufacturer:** Cermate Technologies Inc.  
7F.-1, No.168, Liancheng Rd., Zhonghe Dist.,  
New Taipei City 23553, Taiwan (R.O.C.)

**Tested:** January 15, 2019 & January 19, 2019


<b>Applicable Standards:</b>	<b>EN 61000-6-4: 2007 + A1: 2011</b>	<b>EN 61000-6-2: 2005 / AC: 2005</b>
	<b>EN 61000-3-2: 2014</b>	IEC 61000-4-2: 2008
	<b>EN 61000-3-3: 2013</b>	IEC 61000-4-3: 2006 + A1: 2007 + A2: 2010
		IEC 61000-4-4: 2012
		IEC 61000-4-5: 2014 + A1: 2017
		IEC 61000-4-6: 2013
		IEC 61000-4-8: 2009
		IEC 61000-4-11: 2004 + A1: 2017

## Statements of Conformity

Determination of compliance is based on the results of the compliance measurement, not taking into account measurement instrumentation uncertainty.


The above equipment was tested by Compliance Certification Services Inc. for compliance with the requirements of technical standards specified above under the EMC Directive 2014/30/EU. The results of testing in this report apply only to the product/system, which was tested. Other similar equipment will not necessarily produce the same results due to production tolerance and measurement uncertainties.

**Approved by:**



Sam Hu  
Assistant Manager

**Reviewed by:**



Eva Fan  
Supervisor of report document dept.

## 2 TEST RESULT SUMMARY

EMISSION			
Standard	Item	Result	Remarks
EN 61000-6-4: 2007 + A1: 2011			
CISPR 16-2-1, CISPR 16-1-2	Conducted (Power Port)	PASS	Meet limit
CISPR 22	Conducted (Telecom port)	PASS	Meet limit
CISPR 16-2-3	Radiated	PASS	Meet limit
EN 61000-3-2: 2014	Harmonic current emissions	PASS	Meet Class A limit
EN 61000-3-3: 2013	Voltage fluctuations & flicker	PASS	Meets the requirements

IMMUNITY [ EN 61000-6-2: 2005 / AC: 2005 ]			
Standard	Item	Result	Remarks
IEC 61000-4-2: 2008	ESD	PASS	Meets the requirements of Performance Criterion A
IEC 61000-4-3: 2006 + A1: 2007 + A2: 2010	RS	PASS	Meets the requirements of Performance Criterion A
IEC 61000-4-4: 2012	EFT	PASS	Meets the requirements of Performance Criterion A
IEC 61000-4-5: 2014 + A1: 2017	Surge	PASS	Meets the requirements of Performance Criterion A
IEC 61000-4-6: 2013	CS	PASS	Meets the requirements of Performance Criterion A
IEC 61000-4-8: 2009	PFMF	PASS	Meets the requirements of Performance Criterion A
IEC 61000-4-11: 2004 + A1: 2017	Voltage dips & voltage variations	PASS	Meets the requirements of <b>Voltage Dips:</b> 1) 0% residual Performance Criterion A 2) 40% residual Performance Criterion A 3) 70% residual Performance Criterion A <b>Voltage Interruptions:</b> 1) 0% residual Performance Criterion C

### 3 EUT DESCRIPTION

<b>Product</b>	LCD Touch Control Panel
<b>Brand Name</b>	Cermate
<b>Model</b>	PT2104; KT2104; GT2104; MMPT2104; xPT2104; MT2104; FT2104; FC2104; DAK-2104B; LUI2104; MG-T2104-24; SK2104; eV2104; MT2104; TV2104; AST-2104THSxx; VT92104T; PY2104-AST; PSST2104-AST; PT2104-AST; KT2104-AST; ET2104-AST; ET2104-AST; THM2104A; MZ600-TT2104H; VM12104-AST; VM12104-AS; VM12104-AH; RT2104; RL2104; KT2104; PL2104; KL2104; AS43TFT1025; WOP-2100T; GPT2104; XI33B-T2B; xPT2104; HT2104; AS46TFT1007; CPT2104; PMT2104; IPT2104; IV214M-SEAP; IHM104T2E; IM-PT2104
<b>Applicant</b>	Cermate Technologies Inc.
<b>Housing material</b>	Plastic w/ Metal plate
<b>Identify Number</b>	T190111D10
<b>Received Date</b>	January 11, 2019
<b>EUT Power Rating</b>	24VDC from DC Power Supply

#### Model Differences

Model	Difference	Tested (Check)
PT2104	Original	<input checked="" type="checkbox"/>
KT2104; GT2104; MMPT2104; xPT2104; MT2104; FT2104; FC2104; DAK-2104B; LUI2104; MG-T2104-24; SK2104; eV2104; MT2104; TV2104; AST-2104THSxx; VT92104T; PY2104-AST; PSST2104-AST; PT2104-AST; KT2104-AST; ET2104-AST; ET2104-AST; THM2104A; MZ600-TT2104H; VM12104-AST; VM12104-AS; VM12104-AH; RT2104; RL2104; KT2104; PL2104; KL2104; AS43TFT1025; WOP-2100T; GPT2104; XI33B-T2B; xPT2104; HT2104; AS46TFT1007; CPT2104; PMT2104; IPT2104; IV214M-SEAP; IHM104T2E; IM-PT2104	For marketing purpose only.	<input type="checkbox"/>

#### I/O PORT

I/O PORT TYPES	Q'TY	TESTED WITH
1. COM 1 / COM 3 Port	1	1
2. COM 2 Port	1	1
3. USB Port	2	2
4. LAN Port	1	1
5. SD Card Slot	1	1

**Note:** Client consigns only one model sample to test (Model Number: PT2104).

## 4 TEST METHODOLOGY

### 4.1. DECISION OF FINAL TEST MODE

The EUT was tested together with the below additional components, and a configuration, which produced the worst emission levels, was selected and recorded in this report.

The test configuration/ modes are as the following:

#### Conduction Modes (Power port):

1	AC Power Mode
2	DC Power Mode

#### Conduction Modes (Telecom port):

1	10Mbps
2	100Mbps

#### Radiation Mode:

1	Normal Mode
	Normal Mode / 1-6GHz

#### Worst:

Conduction (Power port): Mode 2

Conduction (Telecom port): Mode 1

Radiation: Mode 1

### 4.2. EUT SYSTEM OPERATION

1. Windows 10 boots system.
2. Press the start menu, select executive and type ping 192.168.10.10 -t (Server Notebook).

**Note:** Test program is self-repeating throughout the test.

## 5 SETUP OF EQUIPMENT UNDER TEST

### 5.1. DESCRIPTION OF SUPPORT UNITS

The EUT has been tested as an independent unit together with other necessary accessories or support units. The following support units or accessories were used to form a representative test configuration during the tests.


#### Peripherals Devices:

No.	Equipment	Model No.	Serial No.	FCC ID / BSMI ID	Brand Name	Data Cable	Power Cord
1	USB HDD	HD-234	N/A	N/A	A-Tec	Shielded, 1.8m with a core	N/A
2	LCD Touch Control Panel	PA2071	N/A	N/A	Cermate	COM: Shielded, 2.0m COM: Shielded, 3.0m	Unshielded, 1.4m
3	DC Power Supply	NES-35-24	N/A	N/A	MEAN WELL	Unshielded, 1.4m	Unshielded, 1.4m
4	SD Card	N/A	N/A	N/A	PQI	N/A	N/A
5	Server Notebook	XPS13	7R0S3G2	DOC BSMI: R31199	DELL	Unshielded, 20m	Unshielded, 1.8m
6	USB Cable	N/A	N/A	N/A	N/A	Shielded, 1.8m	N/A

#### Note:

- 1) All the equipment/cables were placed in the worst-case configuration to maximize the emission during the test.
- 2) Grounding was established in accordance with the manufacturer's requirements and conditions for the intended use.

### 5.2. CONFIGURATION OF SYSTEM UNDER TEST





## 6 FACILITIES AND ACCREDITATIONS

### 6.1. FACILITIES

All measurement facilities used to collect the measurement data are located at CCSrf Taiwan Xindian Lab. at No.163-1, Jhongsheng Rd., Xindian Dist., New Taipei City, 23151 Taiwan.

The sites are constructed in conformance with the requirements of ANSI C63.4 and CISPR Publication 22. All receiving equipment conforms to CISPR 16-1-1, CISPR 16-1-2, CISPR 16-1-3, CISPR 16-1-4 and CISPR 16-1-5.

### 6.2. ACCREDITATIONS

Our laboratories are accredited and approved by the following accreditation body according to ISO/IEC 17025.

<b>Taiwan</b>	TAF
<b>USA</b>	A2LA

The measuring facility of laboratories has been authorized or registered by the following approval agencies.

<b>Canada</b>	Industry Canada
<b>Japan</b>	VCCI
<b>Taiwan</b>	BSMI
<b>USA</b>	FCC

Copies of granted accreditation certificates are available for downloading from our web site, <http://www.ccsrf.com>

### 6.3. MEASUREMENT UNCERTAINTY

Where relevant, the following measurement uncertainty levels have been estimated for tests performed on the EUT as specified in CISPR 16-4-2:

Measurement	Frequency	Uncertainty
Conducted emissions (Power port)	0.15MHz ~ 30MHz	± 2.8
Conducted emissions (Telecom port)	0.15MHz ~ 30MHz	± 3.2
Radiated emissions	30MHz ~ 1000MHz	± 5.3
	1000MHz ~ 6000MHz	± 4.7

This uncertainty represents an expanded uncertainty expressed at approximately the 95% confidence level using a coverage factor of k=2.

Consistent with industry standard (e.g. CISPR 22: 2005, clause 11, Measurement Uncertainty) determining compliance with the limits shall be base on the results of the compliance measurement. Consequently the measure emissions being less than the maximum allowed emission result in this be a compliant test or passing test.

The acceptable measurement uncertainty value without requiring revision of the compliance statement is base on conducted and radiated emissions being less than  $U_{CISPR}$  which is 3.6dB and 5.2dB respectively. CCS values (called  $U_{Lab}$  in CISPR 16-4-2) is less than  $U_{CISPR}$  as shown in the table above. Therefore, MU need not be considered for compliance.

## 7 EMISSION TEST

### 7.1. CONDUCTED EMISSION MEASUREMENT

#### 7.1.1. LIMITS

FREQUENCY (MHz)	dBuV	
	Quasi-peak	Average
0.15 - 0.5	79	66
0.50 - 5.0	73	60
5.0 - 30.0	73	60

**NOTE:** 1. The lower limit shall apply at the transition frequencies.

2. All emanations from digital device or system, including any network of conductors and apparatus connected thereto, shall not exceed the level of field strengths specified above.

#### 7.1.2. TEST INSTRUMENTS

Conducted Emission room # A				
Name of Equipment	Manufacturer	Model	Serial Number	Calibration Due
BNC CABLE	EMEC	EMG178	BNC#A9	03/26/2019
EMI Test Receiver	R&S	ESCI	101201	09/25/2019
LISN	Schwarzbeck	NNLK 8129	8129-286	08/09/2019
LISN(EUT)	Schwarzbeck	NSLK 8127	8127527	08/09/2019
Pulse Limiter	R&S	ESH3Z2	SD-C002	08/15/2019
Thermo-Hygro Meter	Wisewind	201A	No. 02	05/06/2019
Test S/W	EZ-EMC			

**NOTE:** 1. The calibration interval of the above test instruments is 12 months and the calibrations are traceable to NML/ROC and NIST/USA.

2. N.C.R = No Calibration Request.


**7.1.3. TEST PROCEDURES** (please refer to measurement standard or CCS SOP PA-031)**Procedure of Preliminary Test**

- The EUT was set up as per the test configuration to simulate typical usage per the user's manual. When the EUT is a tabletop system, a wooden table with a height of 0.8 meters is used and is placed on the ground plane as per CISPR 16-2-1, 7.4.1 (see Test Facility for the dimensions of the ground plane used). When the EUT is a floor-standing equipment, it is placed on the ground plane which has a 15 cm non-conductive covering to insulate the EUT from the ground plane.
- Support equipment, if needed, was placed as per CISPR 16-2-1, 7.4.1.
- All I/O cables were positioned to simulate typical actual usage as per CISPR 16-2-1, 7.4.1.
- The test equipment EUT installed received AC main power, through a Line Impedance Stabilization Network (LISN), which supplied power source and was grounded to the ground plane.
- All support equipment received power from a second LISN.
- The EUT test program was started. Emissions were measured on each current carrying line of the EUT using an EMI Test Receiver connected to the LISN powering the EUT.
- The Receiver scanned from 150kHz to 30MHz for emissions in each of the test modes.
- During the above scans, the emissions were maximized by cable manipulation.
- The test mode(s) described in Item 4.1 were scanned during the preliminary test.
- After the preliminary scan, we found the test mode described in Item 4.1 producing the highest emission level.
- The EUT configuration and cable configuration of the above highest emission level were recorded for reference of the final test.

**Procedure of Final Test**

- EUT and support equipment were set up on the test bench as per the configuration with highest emission level in the preliminary test.
- A scan was taken on both power lines, Line 1 and Line 2, recording at least the six highest emissions. Emission frequency and amplitude were recorded into a computer in which correction factors were used to calculate the emission level and compare reading to the applicable limit.
- The test data of the worst-case condition(s) was recorded.

## 7.1.4. TEST SETUP



- For the actual test configuration, please refer to the related item – Photographs of the Test Configuration.

## 7.1.5. DATA SAMPLE

Freq. (MHz)	Reading (dBuV)	Factor (dB)	Result (dBuV)	Limit (dBuV)	Margin (dB)	Detector (P/Q/A)	Line (L1/L2)
x.xx	42.95	0.55	43.50	73	-29.50	Q	L1


Freq. = Emission frequency in MHz  
 Reading = Uncorrected Analyzer/Receiver reading  
 Factor = Insertion loss of LISN + Cable Loss + Pulse Limit  
 Result = Read Level + Factor  
 Limit = Limit stated in standard  
 Margin = Reading in reference to limit  
 P = Peak Reading  
 Q = Quasi-peak Reading  
 A = Average Reading  
 L1 = Hot side  
 L2 = Neutral side

### Calculation Formula

Margin (dB) = Result (dBuV) – Limit (dBuV)

### 7.1.6. TEST RESULTS


Model No.	PT2104	6dB Bandwidth	9 kHz
Environmental Conditions	22°C, 63% RH	Test Mode	Mode 1
Tested by	Kevin Chang	Phase	L1
Standard	EN 61000-6-4		



Conducted Emission Readings							
Frequency Range Investigated				150 kHz to 30 MHz			
Freq. (MHz)	Reading (dBuV)	Factor (dB)	Result (dBuV)	Limit (dBuV)	Margin (dB)	Detector (P/Q/A)	Line (L1/L2)
0.2819	41.43	9.95	51.38	79.00	-27.62	P	L1
1.1180	34.62	10.01	44.63	73.00	-28.37	P	L1
1.7660	33.67	10.06	43.73	73.00	-29.27	P	L1
5.2900	33.85	10.27	44.12	73.00	-28.88	P	L1
15.7180	43.55	10.67	54.22	73.00	-18.78	P	L1
25.3540	46.66	10.98	57.64	73.00	-15.36	P	L1

Note: 1. L1 = Line One (Live Line) / L2 = Line Two (Neutral Line).


Model No.	PT2104	6dB Bandwidth	9 kHz
Environmental Conditions	22°C, 63% RH	Test Mode	Mode 1
Tested by	Kevin Chang	Phase	L1
Standard	EN 61000-6-4		



Conducted Emission Readings							
Frequency Range Investigated				150 kHz to 30 MHz			
Freq. (MHz)	Reading (dBuV)	Factor (dB)	Result (dBuV)	Limit (dBuV)	Margin (dB)	Detector (P/Q/A)	Line (L1/L2)
0.2779	41.89	9.96	51.85	79.00	-27.15	P	L2
0.4660	36.25	9.97	46.22	79.00	-32.78	P	L2
1.1180	34.60	10.01	44.61	73.00	-28.39	P	L2
1.7660	33.64	10.05	43.69	73.00	-29.31	P	L2
15.6540	43.30	10.64	53.94	73.00	-19.06	P	L2
25.2900	45.93	10.98	56.91	73.00	-16.09	P	L2

Note: 1. L1 = Line One (Live Line) / L2 = Line Two (Neutral Line).


Model No.	PT2104	6dB Bandwidth	9 kHz
Environmental Conditions	22°C, 63% RH	Test Mode	Mode 2 / Worst
Tested by	Kevin Chang	Phase	L1
Standard	EN 61000-6-4		



Conducted Emission Readings							
Frequency Range Investigated				150 kHz to 30 MHz			
Freq. (MHz)	Reading (dBuV)	Factor (dB)	Result (dBuV)	Limit (dBuV)	Margin (dB)	Detector (P/Q/A)	Line (L1/L2)
0.2100	48.22	9.93	58.15	79.00	-20.85	P	L1
0.2779	39.22	9.95	49.17	79.00	-29.83	P	L1
0.3500	35.31	9.96	45.27	79.00	-33.73	P	L1
4.3900	48.02	10.21	58.23	73.00	-14.77	P	L1
10.0340	46.47	10.48	56.95	73.00	-16.05	P	L1
19.1580	33.01	10.77	43.78	73.00	-29.22	P	L1

Note: 1. L1 = Line One (Live Line) / L2 = Line Two (Neutral Line).

Model No.	PT2104	6dB Bandwidth	9 kHz
Environmental Conditions	22°C, 63% RH	Test Mode	Mode 2 / Worst
Tested by	Kevin Chang	Phase	L2
Standard	EN 61000-6-4		



Conducted Emission Readings							
Frequency Range Investigated				150 kHz to 30 MHz			
Freq. (MHz)	Reading (dBuV)	Factor (dB)	Result (dBuV)	Limit (dBuV)	Margin (dB)	Detector (P/Q/A)	Line (L1/L2)
0.2100	48.51	9.94	58.45	79.00	-20.55	P	L2
0.2779	39.55	9.96	49.51	79.00	-29.49	P	L2
0.3500	35.67	9.96	45.63	79.00	-33.37	P	L2
4.3980	47.59	10.18	57.77	73.00	-15.23	P	L2
9.9819	46.69	10.44	57.13	73.00	-15.87	P	L2
19.6060	32.48	10.77	43.25	73.00	-29.75	P	L2

Note: 1. L1 = Line One (Live Line) / L2 = Line Two (Neutral Line).



## 7.2. CONDUCTED EMISSION MEASUREMENT AT TELECOMMUNICATION PORTS

### 7.2.1. LIMITS

FREQUENCY (MHz)	Voltage Limit (dBuV)		Current Limit (dBuA)	
	Quasi-peak	Average	Quasi-peak	Average
0.15 ~ 0.5	97 ~ 87	84 ~ 74	53 ~ 43	40 ~ 30
0.5 ~ 30.0	87	74	43	30

**NOTE:** 1. At transitional frequencies the lower limit applies.  
 2. The limits decrease linearly with the logarithm of the frequency in the range 0.15 MHz to 0.5 MHz.  
 3. The current and voltage disturbance limits are derived for use with an impedance stabilization network (ISN) which presents a common mode (asymmetric mode) impedance of 150Ω to the telecommunication port under test (conversion factor is  $20 \log_{10} 150 / I = 44$  dB).

### 7.2.2. TEST INSTRUMENTS

Conducted Emission room # A				
Name of Equipment	Manufacturer	Model	Serial Number	Calibration Due
BNC CABLE	EMEC	EMG178	BNC#A9	03/26/2019
EMI Test Receiver	R&S	ESCI	101201	09/25/2019
ISN	Teseq	ISN T800	29449	08/09/2019
LISN	Schwarzbeck	NNLK 8129	8129-286	08/09/2019
LISN(EUT)	Schwarzbeck	NSLK 8127	8127527	08/09/2019
Pulse Limiter	R&S	ESH3Z2	SD-C002	08/15/2019
Thermo-Hygro Meter	Wisewind	201A	No. 02	05/06/2019
Test S/W	EZ-EMC			

**NOTE:** 1. The calibration interval of the above test instruments is 12 months and the calibrations are traceable to NML/ROC and NIST/USA.  
 2. N.C.R = No Calibration Request.


**7.2.3. TEST PROCEDURE** (please refer to measurement standard or CCS SOP PA-031)

- Selecting ISN for unscreened cable or a current probe for screened cable to take measurement.
- The port of the EUT was connected to the remote side support equipment through the ISN/Current Probe and communication in normal condition.
- Making a overall range scan by using the test receiver controlled by controller and record at least six highest emissions for showing in the test report.
- Emission frequency and amplitude were recorded into a computer in which correction factors were used to calculate the emission level and compare reading to the applicable limit.
- In case of measuring on the screened cable, the current limit shall be applied; otherwise the voltage limit should be applied.
- The following test modes was scanned during the preliminary test:

**Modes:**

1	10Mbps
2	100Mbps

- After the preliminary scan, we found the following test mode(s) producing the highest emission level and test data of the worst case was recorded.


**Mode: 1****7.2.4. TEST SETUP****For ISN & Current Probe:**

AE = Associated equipment  
EUT = Equipment under test

1) Distance to the reference groundplane (vertical or horizontal).

2) Distance to the reference groundplane is not critical.

## For Voltage & Current Probe:



AE = Associated equipment  
EUT = Equipment under test

- 1) Distance to the reference groundplane (vertical or horizontal).  
2) Distance to the reference groundplane is not critical.

- For the actual test configuration, please refer to the related item – Photographs of the Test Configuration.

## 7.2.5. DATA SAMPLE

Freq. (MHz)	Reading (dBuV)	Factor (dB)	Result (dBuV)	Limit (dBuV)	Margin (dB)	Detector (P/Q/A)
x.xx	62.95	0.55	63.50	87	-23.50	Q


Freq. = Emission frequency in MHz  
Reading = Uncorrected Analyzer/Receiver reading  
Factor = Insertion loss of LISN + Cable Loss + Pulse Limit  
Result = Reading + Factor  
Limit = Limit stated in standard  
Margin = Reading in reference to limit  
P = Peak Reading  
Q = Quasi-peak Reading  
A = Average Reading

### Calculation Formula

Margin (dB) = Result (dBuV) – Limit (dBuV)

## 7.2.6. TEST RESULTS

Model No.	PT2104	6dB Bandwidth	9 kHz
Environmental Conditions	22°C, 63% RH	Test Mode	Mode 1
Tested by	Kevin Chang	Standard	EN 61000-6-4



Conducted Emission Readings						
Frequency Range Investigated				150 kHz to 30 MHz		
Freq. (MHz)	Reading (dBuV)	Factor (dB)	Result (dBuV)	Limit (dBuV)	Margin (dB)	Detector (P/Q/A)
0.8420	39.67	19.52	59.19	87.00	-27.81	P
1.0339	47.45	19.51	66.96	87.00	-20.04	P
1.0980	44.87	19.50	64.37	87.00	-22.63	P
5.8859	49.69	19.55	69.24	87.00	-17.76	P
7.4380	49.43	19.58	69.01	87.00	-17.99	P
10.0219	50.70	19.64	70.34	87.00	-16.66	P

## 7.3. RADIATED EMISSION MEASUREMENT

### 7.3.1. LIMITS

#### Below 1GHz

FREQUENCY (MHz)	dBuV/m (At 10m)
30 ~ 230	40
230 ~ 1000	47

#### Above 1GHz

FREQUENCY (MHz)	dBuV/m (At 3m)	
	Average	Peak
1000 ~ 3000	56	76
3000 ~ 6000	60	80

**NOTE:** The lower limit shall apply at the transition frequencies.

Highest frequency generated or used within the EUT or on which the EUT operates or tunes (MHz)	Upper frequency of measurement range (MHz)
Less than 108	1000
108-500	2000
500-1000	5000
Above 1000	If the highest internal frequency of the EUT is above 1 GHz, the measurement shall be made up to 6 GHz

### 7.3.2. TEST INSTRUMENTS

Open Area Test Site # H				
Name of Equipment	Manufacturer	Model	Serial Number	Calibration Due
Bilog Antenna	Teseq	CBL 6112D	36995	06/25/2019
Cable	EMEC	CFD400NL-LW	N-Type#H11	08/15/2019
EMI Test Receiver	R&S	ESCI	101340	03/26/2019
Pre-Amplifier	HP	8447D	1937A01554	09/27/2019
Thermo-Hygro Meter	Wisewind	201A	No. 03	05/27/2019
Test S/W	EZ-EMC			
Above 1GHz Used				
Horn Antenna	ETS	3117	00139062	09/13/2019
K-Type Cable x 1m (1-40GHz)	Rosnol	K1K50-UP0264- K1k50-1M	160215-1	11/26/2019
Microflex Cable x 7m (1-18GHz)	Rosnol	A1K50-EW0630- A1k50-700CM	SD-R028	11/26/2019
Pre-Amplifier	HP	8449B	3008A01266	11/25/2019
Signal Analyzer	Agilent	N9010A	MY53440125	12/25/2019
Thermo-Hygro Meter	Wisewind	N/A	SD-R027	09/26/2019
Test S/W	EZ-EMC			

**NOTE:** 1. The calibration interval of the above test instruments is 12 months and the calibrations are traceable to NML/ROC and NIST/USA.

2. N.C.R = No Calibration Request.

**7.3.3. TEST PROCEDURE** (please refer to measurement standard or CCS SOP PA-031)**Procedure of Preliminary Test**


- The equipment was set up as per the test configuration to simulate typical usage per the user's manual. When the EUT is a tabletop system, a wooden turntable with a height of 0.8 meters is used which is placed on the ground plane. When the EUT is a floor-standing equipment, it is placed on the ground plane which has a 15 cm non-conductive covering to insulate the EUT from the ground plane.
- Support equipment, if needed, was placed as per CISPR 16-2-3.
- All I/O cables were positioned to simulate typical usage as per CISPR 16-2-3.
- The EUT received AC power source from the outlet socket under the turntable. All support equipment power received from another socket under the turntable.
- The antenna was placed at 3 or 10 meter away from the EUT as stated in CISPR 16-2-3. The antenna connected to the Spectrum Analyzer via a cable and at times a pre-amplifier would be used.
- The Analyzer / Receiver quickly scanned from 30MHz to 6000MHz. The EUT test program was started. Emissions were scanned and measured rotating the EUT to 360 degrees and positioning the antenna 1 to 4 meters above the ground plane, in both the vertical and the horizontal polarization, to maximize the emission reading level.
- The test mode(s) described in Item 4.1 were scanned during the preliminary test:
- After the preliminary scan, we found the test mode described in Item 4.1 producing the highest emission level.
- The EUT and cable configuration, antenna position, polarization and turntable position of the above highest emission level were recorded for the final test.

**Procedure of Final Test**


- EUT and support equipment were set up on the turntable as per the configuration with highest emission level in the preliminary test.
- The Analyzer / Receiver scanned from 30MHz to 6000MHz. Emissions were scanned and measured rotating the EUT to 360 degrees, varying cable placement and positioning the antenna 1 to 4 meters above the ground plane, in both the vertical and the horizontal polarization, to maximize the emission reading level.
- Recorded at least the six highest emissions. Emission frequency, amplitude, antenna position, polarization and turntable position were recorded into a computer in which correction factors were used to calculate the emission level and compare reading to the applicable limit. Below 1GHz the Q.P. reading and above 1GHz the Peak and Average reading are presented.
- The test data of the worst-case condition(s) was recorded.

## 7.3.4. TEST SETUP

### Below 1GHz



### Above 1GHz



- For the actual test configuration, please refer to the related item – Photographs of the Test Configuration.



### 7.3.5. DATA SAMPLE

#### Below 1GHz

Freq. (MHz)	Reading (dBuV)	Factor (dB/m)	Result (dBuV/m)	Limit (dBuV/m)	Margin (dB)	Detector (P/Q)	Pol. (H/V)
x.xx	14.0	12.2	26.2	40	-13.8	Q	H

#### Above 1GHz

Freq. (MHz)	Reading (dBuV)	Factor (dB/m)	Result (dBuV/m)	Limit (dBuV/m)	Margin (dB)	Detector (P/A)	Pol. (H/V)
x.xx	42.95	0.55	43.50	60	-16.50	A	H

Freq. = Emission frequency in MHz  
 Reading = Uncorrected Analyzer/Receiver reading  
 Factor = Antenna Factor + Cable Loss - Amplifier Gain  
 Result = Reading + Factor  
 Limit = Limit stated in standard  
 Margin = Reading in reference to limit  
 P = Peak Reading  
 Q = Quasi-peak Reading  
 A = Average Reading  
 H = Antenna Polarization: Horizontal  
 V = Antenna Polarization: Vertical


#### Calculation Formula

Margin (dB) = Result (dBuV/m) – Limit (dBuV/m)

## 7.3.6. TEST RESULTS

## Below 1GHz


Model No.	PT2104	Test Mode	Mode 1
Environmental Conditions	25°C, 60% RH	6dB Bandwidth	120 kHz
Antenna Pole	Vertical	Antenna Distance	10m
Detector Function	Quasi-peak.	Tested by	Kevin Chang
Standard	EN 61000-6-4		



Radiated Emission Readings									
Frequency Range Investigated				30 MHz to 1000 MHz at 10m					
Freq. (MHz)	Reading (dBuV)	Factor (dB/m)	Result (dBuV/m)	Limit (dBuV/m)	Margin (dB)	Height (cm)	Degree (°)	Detector (P/Q)	Pol. (H/V)
80.3399	46.70	-13.58	33.12	40.00	-6.88	100	125	Q	V
272.4500	35.80	-6.56	29.24	47.00	-17.76	100	169	Q	V
463.4800	39.30	-1.49	37.81	47.00	-9.19	400	202	Q	V
517.8700	37.60	-0.58	37.02	47.00	-9.98	400	136	Q	V
573.3300	34.80	0.57	35.37	47.00	-11.63	400	265	Q	V
900.0200	33.70	4.00	37.70	47.00	-9.30	400	274	Q	V

Note: 1. P= Peak Reading; Q= Quasi-peak Reading.

Model No.	PT2104	Test Mode	Mode 1
Environmental Conditions	25°C, 60% RH	6dB Bandwidth	120 kHz
Antenna Pole	Horizontal	Antenna Distance	10m
Detector Function	Quasi-peak.	Tested by	Kevin Chang
Standard	EN 61000-6-4		




Radiated Emission Readings									
Frequency Range Investigated					30 MHz to 1000 MHz at 10m				
Freq. (MHz)	Reading (dBuV)	Factor (dB/m)	Result (dBuV/m)	Limit (dBuV/m)	Margin (dB)	Height (cm)	Degree (°)	Detector (P/Q)	Pol. (H/V)
80.6400	36.70	-13.58	23.12	40.00	-16.88	400	136	Q	H
299.9500	35.30	-5.94	29.36	47.00	-17.64	400	225	Q	H
463.4500	36.60	-1.49	35.11	47.00	-11.89	100	157	Q	H
600.0300	33.70	0.38	34.08	47.00	-12.92	100	246	Q	H
654.5200	34.30	1.39	35.69	47.00	-11.31	100	298	Q	H
872.8300	32.40	3.62	36.02	47.00	-10.98	100	204	Q	H

Note: 1. P= Peak Reading; Q= Quasi-peak Reading.

## Above 1GHz


Model No.	PT2104	Test Mode	Mode 1
Environmental Conditions	23°C, 60% RH	6dB Bandwidth	1 MHz
Antenna Pole	Vertical	Antenna Distance	3m
Highest frequency generated or used	300MHz	Upper frequency	6000MHz
Detector Function	Peak and average.	Tested by	Kevin Chang
Standard	EN 61000-6-4		



Radiated Emission Readings							
Frequency Range Investigated				Above 1GHz at 3m			
Freq. (MHz)	Reading (dBuV)	Factor (dB/m)	Result (dBuV/m)	Limit (dBuV/m)	Margin (dB)	Detector (P/A)	Pol. (H/V)
2083.333	46.08	-2.20	43.88	76.00	-32.12	P	V
3241.667	46.18	-1.31	44.87	80.00	-35.13	P	V
4091.667	44.71	0.28	44.99	80.00	-35.01	P	V
4725.000	44.36	1.32	45.68	80.00	-34.32	P	V
5558.333	45.07	1.81	46.88	80.00	-33.12	P	V
5841.667	44.57	2.41	46.98	80.00	-33.02	P	V

Note: 1. P= Peak Reading; A= Average Reading.

Model No.	PT2104	Test Mode	Mode 1
Environmental Conditions	23°C, 60% RH	6dB Bandwidth	1 MHz
Antenna Pole	Horizontal	Antenna Distance	3m
Highest frequency generated or used	300MHz	Upper frequency	6000MHz
Detector Function	Peak and average.	Tested by	Kevin Chang
Standard	EN 61000-6-4		




Radiated Emission Readings							
Frequency Range Investigated				Above 1GHz at 3m			
Freq. (MHz)	Reading (dBuV)	Factor (dB/m)	Result (dBuV/m)	Limit (dBuV/m)	Margin (dB)	Detector (P/A)	Pol. (H/V)
2141.667	45.76	-2.16	43.60	76.00	-32.40	P	H
2616.667	45.52	-1.90	43.62	76.00	-32.38	P	H
3675.000	45.15	-0.65	44.50	80.00	-35.50	P	H
4300.000	44.94	0.81	45.75	80.00	-34.25	P	H
4725.000	45.25	1.32	46.57	80.00	-33.43	P	H
5825.000	44.35	2.37	46.72	80.00	-33.28	P	H

Note: 1. P= Peak Reading; A= Average Reading.

## 966 Chamber Test Data

Job No.:	T190111D10	Polarization:	Vertical
Standard:	EN 61000-6-4	Power Source:	24VDC
Test item:	Radiation Test	Date:	2019/1/15
Company:	Cermate Technologies Inc.	Time:	下午 06:30:44
Model:	PT2104	Temp.(°C)/Hum.(%):	23(°C)/60%
Description:	Normal Mode	Engineer Signature:	Kevin Chang



No.	Frequency (MHz)	Reading (dBuV)	Factor (dB/m)	Result (dBuV/m)	Limit (dBuV/m)	Margin (dB)	Detector	Remark
1	80.4400	62.31	-24.10	38.21	40.00	-1.79	peak	
2	272.5000	50.99	-20.72	30.27	47.00	-16.73	peak	
3	463.5900	57.05	-16.76	40.29	47.00	-6.71	peak	
4	517.9099	55.49	-16.27	39.22	47.00	-7.78	peak	
5	573.2000	49.98	-15.30	34.68	47.00	-12.32	peak	
6	900.0900	48.47	-7.51	40.96	47.00	-6.04	peak	


Report No.: T190625D08-I-E

Ref. No.: T190111D10-E

Page: 31 / 87

Rev.: 01

Job No.:	T190111D10	Polarization:	Horizontal
Standard:	EN 61000-6-4	Power Source:	24VDC
Test item:	Radiation Test	Date:	2019/1/15
Company:	Cermate Technologies Inc.	Time:	下午 06:35:11
Model:	PT2104	Temp.(°C)/Hum.(%):	23(°C)/60%
Description:	Normal Mode	Engineer Signature:	Kevin Chang



No.	Frequency (MHz)	Reading (dBuV)	Factor (dB/m)	Result (dBuV/m)	Limit (dBuV/m)	Margin (dB)	Detector	Remark
1	80.4400	57.03	-30.43	26.60	40.00	-13.40	peak	
2	299.6600	50.55	-21.56	28.99	47.00	-18.01	peak	
3	463.5900	48.09	-14.66	33.43	47.00	-13.57	peak	
4	600.3600	44.44	-13.70	30.74	47.00	-16.26	peak	
5	654.6800	42.83	-13.09	29.74	47.00	-17.26	peak	
6	872.9300	44.77	-12.64	32.13	47.00	-14.87	peak	

## 7.4. HARMONICS CURRENT MEASUREMENT

### 7.4.1. LIMITS OF HARMONICS CURRENT MEASUREMENT

Limits for Class A equipment		Limits for Class D equipment		
Harmonics Order n	Max. permissible harmonics current A	Harmonics Order n	Max. permissible harmonics current per watt mA/W	Max. permissible harmonics current A
Odd harmonics		Odd Harmonics only		
3	2.30	3	3.4	2.30
5	1.14	5	1.9	1.14
7	0.77	7	1.0	0.77
9	0.40	9	0.5	0.40
11	0.33	11	0.35	0.33
13	0.21	13	0.30	0.21
15<=n<=39	0.15x15/n	15<=n<=39	3.85/n	0.15x15/n
Even harmonics				
2	1.08			
4	0.43			
6	0.30			
8<=n<=40	0.23x8/n			

**NOTE:** 1. Class A and Class D are classified according to item 7.4.3.  
 2. According to section 7 of EN 61000-3-2, the above limits for all equipment except for lighting equipment having an active input power > 75 W and no limits apply for equipment with an active input power up to and including 75 W.

### 7.4.2. TEST INSTRUMENTS

Name of Equipment	Manufacturer	Model	Serial Number	Calibration Due
Signal Conditioning Unit	Teseq	NSG 1000-1	1846A01831	12/19/2019
5kVA Power Source	Teseq	NSG 1007-5	1537A01296	12/19/2019
Software	WIN2100V4 Ver. 4.22			

**NOTE:** The calibration interval of the above test instruments is 12 months and the calibrations are traceable to NML/ROC and NIST/USA.



**7.4.3. TEST PROCEDURE** (please refer to measurement standard or CCS SOP PA-029)

- The EUT was placed on the top of a wooden table 0.8 meters above the ground and operated to produce the maximum harmonic components under normal operating conditions for each successive harmonic component in turn.
- The classification of EUT is according to section 5 of EN 61000-3-2.
- The EUT is classified as follows:


Class A: Balanced three-phase equipment, Household appliances excluding equipment as Class D, Tools excluding portable tools, Dimmers for incandescent lamps, audio equipment, equipment not specified in one of the three other classes.

Class B: Portable tools; Arc welding equipment which is not professional equipment.

Class C: Lighting equipment.

Class D: Equipment having a specified power less than or equal to 600 W of the following types: Personal computers and personal computer monitors; television receivers and refrigerators and freezers having one or more variable-speed drives to control compressor motor(s).

- The correspondent test program of test instrument to measure the current harmonics emanated from EUT is chosen. The measure time shall be not less than the time necessary for the EUT to be exercised.

**7.4.4. TEST SETUP**

- For the actual test configuration, please refer to the related item – Photographs of the Test Configuration.

**7.4.5. TEST RESULTS**


<b>Power Consumption</b>	8.1W	<b>Test Results</b>	PASS
<b>Environmental Conditions</b>	20°C, 58% RH, 1009mbar	<b>Limits</b>	Class <input checked="" type="checkbox"/> A <input type="checkbox"/> B <input type="checkbox"/> C <input type="checkbox"/> D
<b>Test Mode</b>	Operating	<b>Tested by</b>	Rax Chen

**NOTE:** 1. Limits classified according to item 7.4.1.

## Test result of EN 61000-3-2


Test Result: Pass      Source qualification: Normal

### Current & voltage waveforms



### Harmonics and Class A limit line

### European Limits



**Test result: Pass**      Worst harmonics H15-8.3% of 150% limit, H15-12.2% of 100% limit

Report No.: T190625D08-I-E

Ref. No.: T190111D10-E

Page: 35 / 87

Rev.: 01

Test Result: Pass Source qualification: Normal  
 THC(A): 0.077 I-THD(%): 138.6 POHC(A): 0.012 POHC Limit(A): 0.251

## Highest parameter values during test:

V_RMS (Volts): 229.85	Frequency(Hz): 50.00
I_Peak (Amps): 0.488	I_RMS (Amps): 0.124
I_Fund (Amps): 0.055	Crest Factor: 3.951
Power (Watts): 8.1	Power Factor: 0.288

Harm#	Harms(avg)	100%Limit	%of Limit	Harms(max)	150%Limit	%of Limit	Status
2	0.004	1.080	N/A	0.005	1.620	N/A	Pass
3	0.034	2.300	1.5	0.035	3.450	1.0	Pass
4	0.004	0.430	N/A	0.004	0.645	N/A	Pass
5	0.032	1.140	2.8	0.033	1.710	1.9	Pass
6	0.003	0.300	N/A	0.004	0.450	N/A	Pass
7	0.030	0.770	3.9	0.031	1.155	2.7	Pass
8	0.003	0.230	N/A	0.003	0.345	N/A	Pass
9	0.028	0.400	7.0	0.028	0.600	4.7	Pass
10	0.003	0.184	N/A	0.003	0.276	N/A	Pass
11	0.025	0.330	7.5	0.025	0.495	5.1	Pass
12	0.002	0.153	N/A	0.002	0.230	N/A	Pass
13	0.022	0.210	10.3	0.022	0.315	7.0	Pass
14	0.002	0.131	N/A	0.002	0.197	N/A	Pass
15	0.018	0.150	12.2	0.019	0.225	8.3	Pass
16	0.001	0.115	N/A	0.001	0.173	N/A	Pass
17	0.015	0.132	11.3	0.015	0.198	7.7	Pass
18	0.001	0.102	N/A	0.001	0.153	N/A	Pass
19	0.012	0.118	9.8	0.012	0.178	6.8	Pass
20	0.001	0.092	N/A	0.001	0.138	N/A	Pass
21	0.009	0.107	8.0	0.009	0.161	5.6	Pass
22	0.001	0.084	N/A	0.001	0.125	N/A	Pass
23	0.006	0.098	5.9	0.006	0.147	4.2	Pass
24	0.001	0.077	N/A	0.001	0.115	N/A	Pass
25	0.003	0.090	N/A	0.004	0.135	N/A	Pass
26	0.001	0.071	N/A	0.001	0.107	N/A	Pass
27	0.002	0.083	N/A	0.002	0.125	N/A	Pass
28	0.002	0.066	N/A	0.003	0.099	N/A	Pass
29	0.002	0.078	N/A	0.002	0.116	N/A	Pass
30	0.001	0.061	N/A	0.001	0.092	N/A	Pass
31	0.002	0.073	N/A	0.002	0.109	N/A	Pass
32	0.002	0.058	N/A	0.003	0.086	N/A	Pass
33	0.002	0.068	N/A	0.003	0.102	N/A	Pass
34	0.001	0.054	N/A	0.001	0.081	N/A	Pass
35	0.003	0.064	N/A	0.003	0.096	N/A	Pass
36	0.001	0.051	N/A	0.001	0.077	N/A	Pass
37	0.003	0.061	N/A	0.003	0.091	N/A	Pass
38	0.000	0.048	N/A	0.001	0.073	N/A	Pass
39	0.002	0.058	N/A	0.003	0.087	N/A	Pass
40	0.000	0.046	N/A	0.000	0.069	N/A	Pass

Test Result: Pass      Source qualification: Normal

Highest parameter values during test:

Voltage (Vrms):	229.85	Frequency(Hz):	50.00
I <sub>Peak</sub> (Amps):	0.488	I <sub>RMS</sub> (Amps):	0.124
I <sub>Fund</sub> (Amps):	0.055	Crest Factor:	3.951
Power (Watts):	8.1	Power Factor:	0.288

Harm#	Harmonics V-rms	Limit V-rms	% of Limit	Status
2	0.073	0.459	15.78	OK
3	0.360	2.068	17.40	OK
4	0.044	0.460	9.53	OK
5	0.071	0.919	7.67	OK
6	0.019	0.460	4.16	OK
7	0.054	0.689	7.77	OK
8	0.011	0.460	2.34	OK
9	0.046	0.460	10.01	OK
10	0.018	0.460	3.81	OK
11	0.016	0.230	7.12	OK
12	0.013	0.230	5.55	OK
13	0.020	0.230	8.55	OK
14	0.006	0.230	2.70	OK
15	0.009	0.230	4.04	OK
16	0.006	0.230	2.60	OK
17	0.014	0.230	6.23	OK
18	0.009	0.230	3.75	OK
19	0.019	0.230	8.25	OK
20	0.026	0.230	11.14	OK
21	0.015	0.230	6.57	OK
22	0.005	0.230	2.14	OK
23	0.015	0.230	6.45	OK
24	0.006	0.230	2.76	OK
25	0.009	0.230	3.84	OK
26	0.005	0.230	2.15	OK
27	0.011	0.230	4.71	OK
28	0.004	0.230	1.88	OK
29	0.011	0.230	4.88	OK
30	0.005	0.230	2.27	OK
31	0.005	0.230	2.14	OK
32	0.004	0.230	1.53	OK
33	0.006	0.230	2.53	OK
34	0.004	0.230	1.58	OK
35	0.010	0.230	4.27	OK
36	0.003	0.230	1.14	OK
37	0.009	0.230	3.74	OK
38	0.003	0.230	1.37	OK
39	0.007	0.230	3.21	OK
40	0.015	0.230	6.57	OK

## 7.5. VOLTAGE FLUCTUATION AND FLICKER MEASUREMENT

### 7.5.1. LIMITS OF VOLTAGE FLUCTUATION AND FLICKER MEASUREMENT

TEST ITEM	LIMIT	REMARK
$P_{st}$	1.0	$P_{st}$ means short-term flicker indicator.
$P_{lt}$	0.65	$P_{lt}$ means long-term flicker indicator.
$T_{dt}$ (ms)	500	$T_{dt}$ means maximum time that $dt$ exceeds 3 %.
$d_{max}$ (%)	4%	$d_{max}$ means maximum relative voltage change.
$dc$ (%)	3.3%	$dc$ means relative steady-state voltage change

### 7.5.2. TEST INSTRUMENTS


Name of Equipment	Manufacturer	Model	Serial Number	Calibration Due
Signal Conditioning Unit	Teseq	NSG 1000-1	1846A01831	12/19/2019
5kVA Power Source	Teseq	NSG 1007-5	1537A01296	12/19/2019
Software	WIN2100V4 Ver. 4.22			

**NOTE:** The calibration interval of the above test instruments is 12 months and the calibrations are traceable to NML/ROC and NIST/USA.

### 7.5.3. TEST PROCEDURE (please refer to measurement standard or CCS SOP PA-030)

- The EUT was placed on the top of a wooden table 0.8 meters above the ground and operated to produce the most unfavorable sequence of voltage changes under normal operating conditions.
- During the flick measurement, the measure time shall include that part of whole operation cycle in which the EUT produce the most unfavorable sequence of voltage changes. The observation period for short-term flicker indicator is 10 minutes and the observation period for long-term flicker indicator is 2 hours.

### 7.5.4. TEST SETUP



- For the actual test configuration, please refer to the related item – Photographs of the Test Configuration.



Report No.: T190625D08-I-E

Ref. No.: T190111D10-E

Page: 38 / 87

Rev.: 01

### 7.5.5. TEST RESULTS

Observation Period (Tp)	10mins	Test Mode	Operating
Environmental Conditions	20°C, 58% RH, 1009mbar	Tested by	Rax Chen

TEST PARAMETER	MEASUREMENT VALUE	LIMIT	REMARK
P <sub>st</sub>	0.064	1.0	PASS
P <sub>lt</sub>	0.028	0.65	PASS
T <sub>dt</sub> (ms)	0	500	PASS
d <sub>max</sub> (%)	0	4%	PASS
dc (%)	0	3.3%	PASS

Note: None.



Report No.: T190625D08-I-E

Ref. No.: T190111D10-E

Page: 39 / 87

Rev.: 01


## Test result of EN 61000-3-3

Test Result: Pass

Status: Test Completed

Pst<sub>i</sub> and limit line

European Limits



Plt and limit line



### Parameter values recorded during the test:

Vrms at the end of test (Volt): 229.74

T-max (mS): 0

Highest dc (%): 0.00

Highest dmax (%): 0.00

Highest Pst (10 min. period): 0.064

Highest Plt (2 hr. period): 0.028

Test limit (mS): 500.0 Pass

Test limit (%): 3.30 Pass

Test limit (%): 4.00 Pass

Test limit: 1.000 Pass

Test limit: 0.650 Pass



## 8 IMMUNITY TEST

### 8.1. GENERAL DESCRIPTION

Product Standard	EN 61000-6-2: 2005 / AC: 2005	
	Test Type	Minimum Requirement
<b>Basic Standard, Specification, and Performance Criterion required</b>	IEC 61000-4-2	Electrostatic Discharge – ESD: 8kV air discharge, 4kV Contact discharge, Performance Criterion B
	IEC 61000-4-3	Radio-Frequency Electromagnetic Field Susceptibility Test – RS: 80 ~1000 MHz, 10V/m, 80% AM(1kHz) 1400 ~2000 MHz, 3V/m, 80% AM(1kHz) 2000 ~2700 MHz, 1V/m, 80% AM(1kHz) Performance Criterion A
	IEC 61000-4-4	Electrical Fast Transient/Burst - EFT, AC / DC Power Port: 2kV, Signal/Control Port: 1kV Performance Criterion B
	IEC 61000-4-5	Surge Immunity Test: 1.2/50 $\mu$ s Open Circuit Voltage, 8 /20 $\mu$ s Short Circuit Current, AC Power Port ~ line to line: 1kV, line to earth: 2kV DC Power Port ~ line to line and line to earth: 0.5kV Signal/Control Port ~ line to earth: 1kV Performance Criterion B
	IEC 61000-4-6	Conducted Radio Frequency Disturbances Test –CS, AC Power Port; DC Power Port; Signal/Control Port: 0.15 ~ 80 MHz, 10Vrms, 80% AM, 1kHz, Performance Criterion A
	IEC 61000-4-8	Power frequency magnetic field immunity test 50Hz/60Hz, 30A/m Performance Criterion A
	IEC 61000-4-11	<b>Voltage Dips:</b> i) 0% residual for 1 cycle, Performance Criterion B ii) 40% residual for 10/12 cycles at 50/60Hz, Performance Criterion C iii) 70% residual for 25/30 cycles at 50/60Hz, Performance Criterion C <b>Voltage Interruptions:</b> 0% residual for 250/300 cycles at 50/60Hz Performance Criterion C



## 8.2. GENERAL PERFORMANCE CRITERIA DESCRIPTION

<b>Criteria A:</b>	The apparatus shall continue to operate as intended during and after the test. No degradation of performance or loss of function is allowed below a performance level specified by the manufacturer, when the apparatus is used as intended. The performance level may be replaced by a permissible loss of performance. If the minimum performance level or the permissible performance loss is not specified by the manufacturer, either of these may be derived from the product description and documentation and what the user may reasonably expect from the apparatus if used as intended.
<b>Criteria B:</b>	The apparatus shall continue to operate as intended after the test. No degradation of performance or loss of function is allowed below a performance level specified by the manufacturer, when the apparatus is used as intended. The performance level may be replaced by a permissible loss of performance. During the test, degradation of performance is however allowed. No change of actual operating state or stored data is allowed. If the minimum performance level or the permissible performance loss is not specified by the manufacturer, either of these may be derived from the product description and documentation and what the user may reasonably expect from the apparatus if used as intended.
<b>Criteria C:</b>	Temporary loss of function is allowed, provided the function is self-recoverable or can be restored by the operation of the controls.

### 8.3. ELECTROSTATIC DISCHARGE (ESD)

#### 8.3.1. TEST SPECIFICATION

**Basic Standard:** IEC 61000-4-2

**Discharge Impedance:** 330 ohm / 150 pF

**Discharge Voltage:** Air Discharge: 2 ; 4 ; 8 kV (Direct)  
Contact Discharge: 2 ; 4 kV (Direct/Indirect)

**Polarity:** Positive & Negative

**Number of Discharge:** Minimum 10 times at each test point

**Discharge Mode:** Single Discharge  
1 second minimum

#### 8.3.2. TEST INSTRUMENT

IMMUNITY SHIELDED ROOM				
Name of Equipment	Manufacturer	Model	Serial Number	Calibration Due
Aneroid Barometer	SATO	7610-20	89090	09/19/2019
ESD Simulator	Teseq	NSG 438	1581	02/07/2019
Thermo-Hygro Meter	Wisewind	N/A	SD-S017	09/26/2019

**NOTE:** The calibration interval of the above test instruments is 12 months and the calibrations are traceable to NML/ROC and NIST/USA.

**8.3.3. TEST PROCEDURE** (please refer to measurement standard or CCS SOP PA-022)

The discharges shall be applied in two ways:

a) Contact discharges to the conductive surfaces and coupling planes:

The EUT shall be exposed to at least 20 discharges, 10 each at negative and positive polarity, at a minimum of four test points. One of the test points shall be subjected to at least 10 indirect discharges to the center of the front edge of the **Horizontal Coupling Plane (HCP)**. The remaining three test points shall each receive at least 10 direct contact discharges. If no direct contact test points are available, then at least 20 indirect discharges shall be applied in the indirect mode. Test shall be performed at a maximum repetition rate of one discharge per second.


b) Air discharges at slots and apertures and insulating surfaces:

On those parts of the EUT where it is not possible to perform contact discharge testing, the equipment should be investigated to identify user accessible points where breakdown may occur. Such points are tested using the air discharge method. This investigation should be restricted to those area normally handled by the user. A minimum of 10 single air discharges shall be applied to the selected test point for each such area.

The basic test procedure was in accordance with IEC 61000-4-2:

- a) The EUT was located 0.1 m minimum from all side of the **HCP** (dimensions 1.6m x 0.8m).
- b) The support units were located another table 30 cm away from the EUT, but direct support unit was/were located at same location as EUT on the HCP and keep at a distance of 10 cm with EUT.
- c) The time interval between two successive single discharges was at least 1 second.
- d) Contact discharges were applied to the non-insulating coating, with the pointed tip of the generator penetrating the coating and contacting the conducting substrate.
- e) Air discharges were applied with the round discharge tip of the discharge electrode approaching the EUT as fast as possible (without causing mechanical damage) to touch the EUT. After each discharge, the ESD generator was removed from the EUT and re-triggered for a new single discharge. The test was repeated until all discharges were complete.
- f) At least ten single discharges (in the most sensitive polarity) were applied at the front edge of each **HCP** opposite the center point of each unit of the EUT and 0.1 meters from the front of the EUT. The long axis of the discharge electrode was in the plane of the **HCP** and perpendicular to its front edge during the discharge.
- g) At least ten single discharges (in the most sensitive polarity) were applied to the center of one vertical edge of the **Vertical Coupling Plane (VCP)** in sufficiently different positions that the four faces of the EUT were completely illuminated. The **VCP** (dimensions 0.5m x 0.5m) was placed vertically to and 0.1 meters from the EUT.

### 8.3.4. TEST SETUP



- For the actual test configuration, please refer to the related item – Photographs of the Test Configuration.

#### NOTE:

##### TABLE-TOP EQUIPMENT

The configuration consisted of a wooden table 0.8 meters high standing on the **Ground Reference Plane**. The **GRP** consisted of a sheet of aluminum at least 0.25mm thick, and 2.5 meters square connected to the protective grounding system. A **Horizontal Coupling Plane** (1.6m x 0.8m) was placed on the table and attached to the **GRP** by means of a cable with 940k Ohm total impedance. The equipment under test, was installed in a representative system as described in section 7 of IEC 61000-4-2, and its cables were placed on the **HCP** and isolated by an insulating support of 0.5mm thickness. A distance of 1-meter minimum was provided between the EUT and the walls of the laboratory and any other metallic structure.

##### FLOOR-STANDING EQUIPMENT

The equipment under test was installed in a representative system as described in section 7 of IEC 61000-4-2, and its cables were isolated from the Ground Reference Plane by an insulating support of 0.1-meter thickness. The GRP consisted of a sheet of aluminum that is at least 0.25mm thick, and 2.5 meters square connected to the protective grounding system and extended at least 0.5 meters from the EUT on all sides.

## 8.3.5. TEST RESULTS

## AC Power

Temperature	19°C	Humidity	57% RH
Pressure	1010mbar	Tested By	Stanley Cheng
Required Passing Performance		Criterion B	

Air Discharge								
Test Points	Test Levels			Results				
	± 2 kV	± 4 kV	± 8 kV	Pass	Fail	Performance Criterion		Observation
Front	<input checked="" type="checkbox"/>	<input checked="" type="checkbox"/>	<input checked="" type="checkbox"/>	<input checked="" type="checkbox"/>	<input type="checkbox"/>	<input checked="" type="checkbox"/> A	<input type="checkbox"/> B	Note <input type="checkbox"/> 1 <input checked="" type="checkbox"/> 2
Back	<input checked="" type="checkbox"/>	<input checked="" type="checkbox"/>	<input checked="" type="checkbox"/>	<input checked="" type="checkbox"/>	<input type="checkbox"/>	<input checked="" type="checkbox"/> A	<input type="checkbox"/> B	Note <input checked="" type="checkbox"/> 1 <input type="checkbox"/> 2
Left	<input checked="" type="checkbox"/>	<input checked="" type="checkbox"/>	<input checked="" type="checkbox"/>	<input checked="" type="checkbox"/>	<input type="checkbox"/>	<input checked="" type="checkbox"/> A	<input type="checkbox"/> B	Note <input type="checkbox"/> 1 <input checked="" type="checkbox"/> 2
Right	<input checked="" type="checkbox"/>	<input checked="" type="checkbox"/>	<input checked="" type="checkbox"/>	<input checked="" type="checkbox"/>	<input type="checkbox"/>	<input checked="" type="checkbox"/> A	<input type="checkbox"/> B	Note <input type="checkbox"/> 1 <input checked="" type="checkbox"/> 2
Bottom	<input checked="" type="checkbox"/>	<input checked="" type="checkbox"/>	<input checked="" type="checkbox"/>	<input checked="" type="checkbox"/>	<input type="checkbox"/>	<input checked="" type="checkbox"/> A	<input type="checkbox"/> B	Note <input type="checkbox"/> 1 <input checked="" type="checkbox"/> 2

Contact Discharge								
Test Points	Test Levels			Results				
	± 2 kV	± 4 kV	± 8 kV	Pass	Fail	Performance Criterion		Observation
Back	<input checked="" type="checkbox"/>	<input checked="" type="checkbox"/>	<input type="checkbox"/>	<input checked="" type="checkbox"/>	<input type="checkbox"/>	<input checked="" type="checkbox"/> A	<input type="checkbox"/> B	Note <input type="checkbox"/> 1 <input checked="" type="checkbox"/> 2
Bottom	<input checked="" type="checkbox"/>	<input checked="" type="checkbox"/>	<input type="checkbox"/>	<input checked="" type="checkbox"/>	<input type="checkbox"/>	<input checked="" type="checkbox"/> A	<input type="checkbox"/> B	Note <input checked="" type="checkbox"/> 1 <input type="checkbox"/> 2

Discharge To Horizontal Coupling Plane								
Side of EUT	Test Levels			Results				
	± 2 kV	± 4 kV	± 8 kV	Pass	Fail	Performance Criterion		Observation
Front	<input checked="" type="checkbox"/>	<input checked="" type="checkbox"/>	<input type="checkbox"/>	<input checked="" type="checkbox"/>	<input type="checkbox"/>	<input checked="" type="checkbox"/> A	<input type="checkbox"/> B	Note <input checked="" type="checkbox"/> 1 <input type="checkbox"/> 2
Back	<input checked="" type="checkbox"/>	<input checked="" type="checkbox"/>	<input type="checkbox"/>	<input checked="" type="checkbox"/>	<input type="checkbox"/>	<input checked="" type="checkbox"/> A	<input type="checkbox"/> B	Note <input checked="" type="checkbox"/> 1 <input type="checkbox"/> 2
Left	<input checked="" type="checkbox"/>	<input checked="" type="checkbox"/>	<input type="checkbox"/>	<input checked="" type="checkbox"/>	<input type="checkbox"/>	<input checked="" type="checkbox"/> A	<input type="checkbox"/> B	Note <input checked="" type="checkbox"/> 1 <input type="checkbox"/> 2
Right	<input checked="" type="checkbox"/>	<input checked="" type="checkbox"/>	<input type="checkbox"/>	<input checked="" type="checkbox"/>	<input type="checkbox"/>	<input checked="" type="checkbox"/> A	<input type="checkbox"/> B	Note <input checked="" type="checkbox"/> 1 <input type="checkbox"/> 2

Discharge To Vertical Coupling Plane								
Side of EUT	Test Levels			Results				
	± 2 kV	± 4 kV	± 8 kV	Pass	Fail	Performance Criterion		Observation
Front	<input checked="" type="checkbox"/>	<input checked="" type="checkbox"/>	<input type="checkbox"/>	<input checked="" type="checkbox"/>	<input type="checkbox"/>	<input checked="" type="checkbox"/> A	<input type="checkbox"/> B	Note <input checked="" type="checkbox"/> 1 <input type="checkbox"/> 2
Back	<input checked="" type="checkbox"/>	<input checked="" type="checkbox"/>	<input type="checkbox"/>	<input checked="" type="checkbox"/>	<input type="checkbox"/>	<input checked="" type="checkbox"/> A	<input type="checkbox"/> B	Note <input checked="" type="checkbox"/> 1 <input type="checkbox"/> 2
Left	<input checked="" type="checkbox"/>	<input checked="" type="checkbox"/>	<input type="checkbox"/>	<input checked="" type="checkbox"/>	<input type="checkbox"/>	<input checked="" type="checkbox"/> A	<input type="checkbox"/> B	Note <input checked="" type="checkbox"/> 1 <input type="checkbox"/> 2
Right	<input checked="" type="checkbox"/>	<input checked="" type="checkbox"/>	<input type="checkbox"/>	<input checked="" type="checkbox"/>	<input type="checkbox"/>	<input checked="" type="checkbox"/> A	<input type="checkbox"/> B	Note <input checked="" type="checkbox"/> 1 <input type="checkbox"/> 2

**NOTE:** 1. There was no change compared with initial operation during the test.  
2. No discharge point.

## DC Power

Temperature	19°C	Humidity	57% RH
Pressure	1010mbar	Tested By	Stanley Cheng
Required Passing Performance		Criterion B	

Air Discharge								
Test Points	Test Levels			Results				
	± 2 kV	± 4 kV	± 8 kV	Pass	Fail	Performance Criterion		Observation
Front	<input checked="" type="checkbox"/>	<input checked="" type="checkbox"/>	<input checked="" type="checkbox"/>	<input checked="" type="checkbox"/>	<input type="checkbox"/>	<input checked="" type="checkbox"/> A	<input type="checkbox"/> B	Note <input type="checkbox"/> 1 <input checked="" type="checkbox"/> 2
Back	<input checked="" type="checkbox"/>	<input checked="" type="checkbox"/>	<input checked="" type="checkbox"/>	<input checked="" type="checkbox"/>	<input type="checkbox"/>	<input checked="" type="checkbox"/> A	<input type="checkbox"/> B	Note <input checked="" type="checkbox"/> 1 <input type="checkbox"/> 2
Left	<input checked="" type="checkbox"/>	<input checked="" type="checkbox"/>	<input checked="" type="checkbox"/>	<input checked="" type="checkbox"/>	<input type="checkbox"/>	<input checked="" type="checkbox"/> A	<input type="checkbox"/> B	Note <input type="checkbox"/> 1 <input checked="" type="checkbox"/> 2
Right	<input checked="" type="checkbox"/>	<input checked="" type="checkbox"/>	<input checked="" type="checkbox"/>	<input checked="" type="checkbox"/>	<input type="checkbox"/>	<input checked="" type="checkbox"/> A	<input type="checkbox"/> B	Note <input type="checkbox"/> 1 <input checked="" type="checkbox"/> 2
Bottom	<input checked="" type="checkbox"/>	<input checked="" type="checkbox"/>	<input checked="" type="checkbox"/>	<input checked="" type="checkbox"/>	<input type="checkbox"/>	<input checked="" type="checkbox"/> A	<input type="checkbox"/> B	Note <input type="checkbox"/> 1 <input checked="" type="checkbox"/> 2

Contact Discharge								
Test Points	Test Levels			Results				
	± 2 kV	± 4 kV	± 8 kV	Pass	Fail	Performance Criterion		Observation
Back	<input checked="" type="checkbox"/>	<input checked="" type="checkbox"/>	<input type="checkbox"/>	<input checked="" type="checkbox"/>	<input type="checkbox"/>	<input checked="" type="checkbox"/> A	<input type="checkbox"/> B	Note <input type="checkbox"/> 1 <input checked="" type="checkbox"/> 2
Bottom	<input checked="" type="checkbox"/>	<input checked="" type="checkbox"/>	<input type="checkbox"/>	<input checked="" type="checkbox"/>	<input type="checkbox"/>	<input checked="" type="checkbox"/> A	<input type="checkbox"/> B	Note <input checked="" type="checkbox"/> 1 <input type="checkbox"/> 2

Discharge To Horizontal Coupling Plane								
Side of EUT	Test Levels			Results				
	± 2 kV	± 4 kV	± 8 kV	Pass	Fail	Performance Criterion		Observation
Front	<input checked="" type="checkbox"/>	<input checked="" type="checkbox"/>	<input type="checkbox"/>	<input checked="" type="checkbox"/>	<input type="checkbox"/>	<input checked="" type="checkbox"/> A	<input type="checkbox"/> B	Note <input checked="" type="checkbox"/> 1 <input type="checkbox"/> 2
Back	<input checked="" type="checkbox"/>	<input checked="" type="checkbox"/>	<input type="checkbox"/>	<input checked="" type="checkbox"/>	<input type="checkbox"/>	<input checked="" type="checkbox"/> A	<input type="checkbox"/> B	Note <input checked="" type="checkbox"/> 1 <input type="checkbox"/> 2
Left	<input checked="" type="checkbox"/>	<input checked="" type="checkbox"/>	<input type="checkbox"/>	<input checked="" type="checkbox"/>	<input type="checkbox"/>	<input checked="" type="checkbox"/> A	<input type="checkbox"/> B	Note <input checked="" type="checkbox"/> 1 <input type="checkbox"/> 2
Right	<input checked="" type="checkbox"/>	<input checked="" type="checkbox"/>	<input type="checkbox"/>	<input checked="" type="checkbox"/>	<input type="checkbox"/>	<input checked="" type="checkbox"/> A	<input type="checkbox"/> B	Note <input checked="" type="checkbox"/> 1 <input type="checkbox"/> 2

Discharge To Vertical Coupling Plane								
Side of EUT	Test Levels			Results				
	± 2 kV	± 4 kV	± 8 kV	Pass	Fail	Performance Criterion		Observation
Front	<input checked="" type="checkbox"/>	<input checked="" type="checkbox"/>	<input type="checkbox"/>	<input checked="" type="checkbox"/>	<input type="checkbox"/>	<input checked="" type="checkbox"/> A	<input type="checkbox"/> B	Note <input checked="" type="checkbox"/> 1 <input type="checkbox"/> 2
Back	<input checked="" type="checkbox"/>	<input checked="" type="checkbox"/>	<input type="checkbox"/>	<input checked="" type="checkbox"/>	<input type="checkbox"/>	<input checked="" type="checkbox"/> A	<input type="checkbox"/> B	Note <input checked="" type="checkbox"/> 1 <input type="checkbox"/> 2
Left	<input checked="" type="checkbox"/>	<input checked="" type="checkbox"/>	<input type="checkbox"/>	<input checked="" type="checkbox"/>	<input type="checkbox"/>	<input checked="" type="checkbox"/> A	<input type="checkbox"/> B	Note <input checked="" type="checkbox"/> 1 <input type="checkbox"/> 2
Right	<input checked="" type="checkbox"/>	<input checked="" type="checkbox"/>	<input type="checkbox"/>	<input checked="" type="checkbox"/>	<input type="checkbox"/>	<input checked="" type="checkbox"/> A	<input type="checkbox"/> B	Note <input checked="" type="checkbox"/> 1 <input type="checkbox"/> 2

**NOTE:** 1. There was no change compared with initial operation during the test.  
2. No discharge point.

## The Photo for Discharge Points of EUT

### Back



### Bottom



Red Dot —Air Discharged  
Blue Dot —Contact Discharged



## 8.4. RADIATED, RADIO-FREQUENCY, ELECTROMAGNETIC FIELD (RS)

### 8.4.1. TEST SPECIFICATION

**Basic Standard:** IEC 61000-4-3

**Frequency Range:** 80 ~ 1000 MHz, 1400 ~ 2000 MHz, 2000 ~ 2700 MHz

**Field Strength:** 10 V/m, 3 V/m, 1 V/m

**Modulation:** 1kHz Sine Wave, 80%, AM Modulation

**Frequency Step:** 1 % of preceding frequency value

**Polarity of Antenna:** Horizontal and Vertical

**Test Distance:** 3 m

**Antenna Height:** 1.5 m

### 8.4.2. TEST INSTRUMENT

844 RS Chamber				
Name of Equipment	Manufacturer	Model	Serial Number	Calibration Due
Electric Field Probe	AR	FL7006	0338955	04/03/2019
Field of Calibration	CCS	Chamber#RS	80-1000MHz	05/01/2019
Power Sensor	Boonton	51013-4E	35812	02/08/2019
RF Power Meter	Boonton	4242-01-02	14357	02/08/2019
Thermo-Hygro Meter	Wisewind	N/A	SD-S019	10/28/2019
Broadband Antenna	AR	AT1080	311819	N.C.R
Power Amplifier	Milmega	80RF1000-600	1079361	N.C.R
Signal Generator	Agilent	N5181A	MY47421336	11/18/2019
Field of Calibration	CCS	Chamber#RS	1-3GHz	03/12/2019
Direction Coupler	AR	DC7200	0343647	N.C.R
Horn Antenna	EMCO	3115	5761	N.C.R
Power Amplifier	AR	60S1G3	302728	N.C.R
Software	Emcware Ver. 2.6.0.16			

**NOTE:** 1. The calibration interval of the above test instruments is 12 months and the calibrations are traceable to NML/ROC and NIST/USA.


2. N.C.R.= No Calibration required.



**8.4.3. TEST PROCEDURE** (please refer to measurement standard or CCS SOP PA-023)

The test procedure was in accordance with IEC 61000-4-3

- The testing was performed in a fully anechoic chamber. The transmit antenna was located at a distance of 3 meter from the EUT.
- The frequency range is swept from 80 MHz to 2700 MHz, with the signal 80% amplitude modulated with a 1kHz sine-wave. The rate of sweep did not exceed  $1.5 \times 10^{-3}$  decade/s, where the frequency range is swept incrementally, the step size was 1% of preceding frequency value.
- The dwell time at each frequency shall be not less than the time necessary for the EUT to be able to respond.
- The test was performed with the EUT exposed to both vertically and horizontally polarized fields on each of the four sides.

**8.4.4. TEST SETUP**

- For the actual test configuration, please refer to the related item – Photographs of the Test Configuration.

**NOTE:****TABLETOP EQUIPMENT**

The EUT installed in a representative system as described in section 7 of IEC 61000-4-3 was placed on a non-conductive table 0.8 meters in height. The system under test was connected to the power and signal wire according to relevant installation instructions.

**FLOOR STANDING EQUIPMENT**

The EUT installed in a representative system as described in section 7 of IEC 61000-4-3 was placed on a non-conductive wood support 0.1 meters in height. The system under test was connected to the power and signal wire according to relevant installation instructions.

### 8.4.5. TEST RESULTS

#### AC Power

<b>Temperature</b>	20°C	<b>Humidity</b>	58% RH
<b>Pressure</b>	1010mbar	<b>Dwell Time</b>	3 sec.
<b>Tested By</b>	Kevin Chang	<b>Required Passing Performance</b>	<b>Criterion A</b>

Frequency (MHz)	Polarity	Azimuth	Field Strength (V/m)	Performance Criterion	Observation	Result
80 ~ 1000	V&H	0	10	<input checked="" type="checkbox"/> A <input type="checkbox"/> B	Note <input checked="" type="checkbox"/> 1 <input type="checkbox"/> 2	PASS
80 ~ 1000	V&H	90	10	<input checked="" type="checkbox"/> A <input type="checkbox"/> B	Note <input checked="" type="checkbox"/> 1 <input type="checkbox"/> 2	PASS
80 ~ 1000	V&H	180	10	<input checked="" type="checkbox"/> A <input type="checkbox"/> B	Note <input checked="" type="checkbox"/> 1 <input type="checkbox"/> 2	PASS
80 ~ 1000	V&H	270	10	<input checked="" type="checkbox"/> A <input type="checkbox"/> B	Note <input checked="" type="checkbox"/> 1 <input type="checkbox"/> 2	PASS
1400 ~ 2000	V&H	0	3	<input checked="" type="checkbox"/> A <input type="checkbox"/> B	Note <input checked="" type="checkbox"/> 1 <input type="checkbox"/> 2	PASS
1400 ~ 2000	V&H	90	3	<input checked="" type="checkbox"/> A <input type="checkbox"/> B	Note <input checked="" type="checkbox"/> 1 <input type="checkbox"/> 2	PASS
1400 ~ 2000	V&H	180	3	<input checked="" type="checkbox"/> A <input type="checkbox"/> B	Note <input checked="" type="checkbox"/> 1 <input type="checkbox"/> 2	PASS
1400 ~ 2000	V&H	270	3	<input checked="" type="checkbox"/> A <input type="checkbox"/> B	Note <input checked="" type="checkbox"/> 1 <input type="checkbox"/> 2	PASS
2000 ~ 2700	V&H	0	1	<input checked="" type="checkbox"/> A <input type="checkbox"/> B	Note <input checked="" type="checkbox"/> 1 <input type="checkbox"/> 2	PASS
2000 ~ 2700	V&H	90	1	<input checked="" type="checkbox"/> A <input type="checkbox"/> B	Note <input checked="" type="checkbox"/> 1 <input type="checkbox"/> 2	PASS
2000 ~ 2700	V&H	180	1	<input checked="" type="checkbox"/> A <input type="checkbox"/> B	Note <input checked="" type="checkbox"/> 1 <input type="checkbox"/> 2	PASS
2000 ~ 2700	V&H	270	1	<input checked="" type="checkbox"/> A <input type="checkbox"/> B	Note <input checked="" type="checkbox"/> 1 <input type="checkbox"/> 2	PASS

**NOTE:** 1. There was no change compared with the initial operation during the test.

## DC Power

Temperature	20°C	Humidity	58% RH
Pressure	1010mbar	Dwell Time	3 sec.
Tested By	Kevin Chang	Required Passing Performance	Criterion A

Frequency (MHz)	Polarity	Azimuth	Field Strength (V/m)	Performance Criterion	Observation	Result
80 ~ 1000	V&H	0	10	<input checked="" type="checkbox"/> A <input type="checkbox"/> B	Note <input checked="" type="checkbox"/> 1 <input type="checkbox"/> 2	PASS
80 ~ 1000	V&H	90	10	<input checked="" type="checkbox"/> A <input type="checkbox"/> B	Note <input checked="" type="checkbox"/> 1 <input type="checkbox"/> 2	PASS
80 ~ 1000	V&H	180	10	<input checked="" type="checkbox"/> A <input type="checkbox"/> B	Note <input checked="" type="checkbox"/> 1 <input type="checkbox"/> 2	PASS
80 ~ 1000	V&H	270	10	<input checked="" type="checkbox"/> A <input type="checkbox"/> B	Note <input checked="" type="checkbox"/> 1 <input type="checkbox"/> 2	PASS
1400 ~ 2000	V&H	0	3	<input checked="" type="checkbox"/> A <input type="checkbox"/> B	Note <input checked="" type="checkbox"/> 1 <input type="checkbox"/> 2	PASS
1400 ~ 2000	V&H	90	3	<input checked="" type="checkbox"/> A <input type="checkbox"/> B	Note <input checked="" type="checkbox"/> 1 <input type="checkbox"/> 2	PASS
1400 ~ 2000	V&H	180	3	<input checked="" type="checkbox"/> A <input type="checkbox"/> B	Note <input checked="" type="checkbox"/> 1 <input type="checkbox"/> 2	PASS
1400 ~ 2000	V&H	270	3	<input checked="" type="checkbox"/> A <input type="checkbox"/> B	Note <input checked="" type="checkbox"/> 1 <input type="checkbox"/> 2	PASS
2000 ~ 2700	V&H	0	1	<input checked="" type="checkbox"/> A <input type="checkbox"/> B	Note <input checked="" type="checkbox"/> 1 <input type="checkbox"/> 2	PASS
2000 ~ 2700	V&H	90	1	<input checked="" type="checkbox"/> A <input type="checkbox"/> B	Note <input checked="" type="checkbox"/> 1 <input type="checkbox"/> 2	PASS
2000 ~ 2700	V&H	180	1	<input checked="" type="checkbox"/> A <input type="checkbox"/> B	Note <input checked="" type="checkbox"/> 1 <input type="checkbox"/> 2	PASS
2000 ~ 2700	V&H	270	1	<input checked="" type="checkbox"/> A <input type="checkbox"/> B	Note <input checked="" type="checkbox"/> 1 <input type="checkbox"/> 2	PASS

**NOTE:** 1. There was no change compared with the initial operation during the test.

## 8.5. ELECTRICAL FAST TRANSIENT (EFT)

### 8.5.1. TEST SPECIFICATION

<b>Basic Standard:</b>	IEC 61000-4-4
<b>Test Voltage:</b>	AC/DC Power Port: 2kV Signal/Control Port: 1kV
<b>Polarity:</b>	Positive & Negative
<b>Impulse Frequency:</b>	5 kHz
<b>Impulse Wave-shape:</b>	5/50 ns
<b>Burst Duration:</b>	15 ms
<b>Burst Period:</b>	300 ms
<b>Test Duration:</b>	Not less than 1 min.

### 8.5.2. TEST INSTRUMENT


Immunity Shield Room				
Name of Equipment	Manufacturer	Model	Serial Number	Calibration Due
Capacitive Clamp	EMC-Partner	CN-EFT1000	589	07/08/2019
EMC Immunity Tester	EMC Partner	TRANSINT 2000	1117	03/13/2019
Software	Genecs Ver. 3.27			

**NOTE:** 1. The calibration interval of the above test instruments is 12 months and the calibrations are traceable to NML/ROC and NIST/USA.  
2. N.C.R.= No Calibration required.

### 8.5.3. TEST PROCEDURE (please refer to measurement standard or CCS SOP PA-024)

- All types of cables, including their length, and the interface port of the EUT to which they were connected.
- Both positive and negative polarity discharges were applied.
- The length of the "hot wire" from the coaxial output of the EFT generator to the terminals on the EUT should not exceed 0.5 meter.
- The duration time of each test sequential was 1 minute.
- The transient/burst waveform was in accordance with IEC 61000-4-4, 5/50ns.

#### 8.5.4. TEST SETUP



- For the actual test configuration, please refer to the related item – Photographs of the Test Configuration.

#### NOTE:

##### TABLETOP EQUIPMENT

The configuration consisted of a wooden table (0.1m high) standing on the Ground Reference Plane. The GRP consisted of a sheet of aluminum (at least 0.25mm thick and 2.5m square) connected to the protective grounding system. A minimum distance of 0.5m was provided between the EUT and the walls of the laboratory or any other metallic structure.

##### FLOOR STANDING EQUIPMENT

The EUT installed in a representative system as described in section 7 of IEC 61000-4-4 and its cables, were isolated from the Ground Reference Plane by an insulating support that is 0.1-meter thick. The GRP consisted of a sheet of aluminum (at least 0.25mm thick and 2.5m square) connected to the protective grounding system.

### 8.5.5. TEST RESULTS

#### AC Power

Temperature	19°C	Humidity	57% RH
Pressure	1010mbar	Tested By	Kevin Chang
Required Passing Performance		Criterion B	

Test Point	Polarity	Test Level (kV)	Performance Criterion	Observation	Result
L	+/-	2	<input checked="" type="checkbox"/> A <input type="checkbox"/> B	Note <input checked="" type="checkbox"/> 1 <input type="checkbox"/> 2	PASS
N	+/-	2	<input checked="" type="checkbox"/> A <input type="checkbox"/> B	Note <input checked="" type="checkbox"/> 1 <input type="checkbox"/> 2	PASS
L-N	+/-	2	<input checked="" type="checkbox"/> A <input type="checkbox"/> B	Note <input checked="" type="checkbox"/> 1 <input type="checkbox"/> 2	PASS
PE	+/-	2	<input checked="" type="checkbox"/> A <input type="checkbox"/> B	Note <input checked="" type="checkbox"/> 1 <input type="checkbox"/> 2	PASS
L - PE	+/-	2	<input checked="" type="checkbox"/> A <input type="checkbox"/> B	Note <input checked="" type="checkbox"/> 1 <input type="checkbox"/> 2	PASS
N - PE	+/-	2	<input checked="" type="checkbox"/> A <input type="checkbox"/> B	Note <input checked="" type="checkbox"/> 1 <input type="checkbox"/> 2	PASS
L - N - PE	+/-	2	<input checked="" type="checkbox"/> A <input type="checkbox"/> B	Note <input checked="" type="checkbox"/> 1 <input type="checkbox"/> 2	PASS
RJ45	+/-	1	<input checked="" type="checkbox"/> A <input type="checkbox"/> B	Note <input checked="" type="checkbox"/> 1 <input type="checkbox"/> 2	PASS
COM 1 / COM 3	+/-	1	<input checked="" type="checkbox"/> A <input type="checkbox"/> B	Note <input checked="" type="checkbox"/> 1 <input type="checkbox"/> 2	PASS
COM 2	+/-	1	<input checked="" type="checkbox"/> A <input type="checkbox"/> B	Note <input checked="" type="checkbox"/> 1 <input type="checkbox"/> 2	PASS

NOTE: 1. There was no change compared with initial operation during the test.

#### DC Power

Temperature	19°C	Humidity	57% RH
Pressure	1010mbar	Tested By	Kevin Chang
Required Passing Performance		Criterion B	

Test Point	Polarity	Test Level (kV)	Performance Criterion	Observation	Result
L	+/-	2	<input checked="" type="checkbox"/> A <input type="checkbox"/> B	Note <input checked="" type="checkbox"/> 1 <input type="checkbox"/> 2	PASS
N	+/-	2	<input checked="" type="checkbox"/> A <input type="checkbox"/> B	Note <input checked="" type="checkbox"/> 1 <input type="checkbox"/> 2	PASS
L-N	+/-	2	<input checked="" type="checkbox"/> A <input type="checkbox"/> B	Note <input checked="" type="checkbox"/> 1 <input type="checkbox"/> 2	PASS
PE	+/-	2	<input checked="" type="checkbox"/> A <input type="checkbox"/> B	Note <input checked="" type="checkbox"/> 1 <input type="checkbox"/> 2	PASS
L - PE	+/-	2	<input checked="" type="checkbox"/> A <input type="checkbox"/> B	Note <input checked="" type="checkbox"/> 1 <input type="checkbox"/> 2	PASS
N - PE	+/-	2	<input checked="" type="checkbox"/> A <input type="checkbox"/> B	Note <input checked="" type="checkbox"/> 1 <input type="checkbox"/> 2	PASS
L - N - PE	+/-	2	<input checked="" type="checkbox"/> A <input type="checkbox"/> B	Note <input checked="" type="checkbox"/> 1 <input type="checkbox"/> 2	PASS
RJ45	+/-	1	<input checked="" type="checkbox"/> A <input type="checkbox"/> B	Note <input checked="" type="checkbox"/> 1 <input type="checkbox"/> 2	PASS
COM 1 / COM 3	+/-	1	<input checked="" type="checkbox"/> A <input type="checkbox"/> B	Note <input checked="" type="checkbox"/> 1 <input type="checkbox"/> 2	PASS
COM 2	+/-	1	<input checked="" type="checkbox"/> A <input type="checkbox"/> B	Note <input checked="" type="checkbox"/> 1 <input type="checkbox"/> 2	PASS

NOTE: 1. There was no change compared with initial operation during the test.

## 8.6. SURGE IMMUNITY TEST

### 8.6.1. TEST SPECIFICATION

<b>Basic Standard:</b>	IEC 61000-4-5
<b>Wave-Shape:</b>	Combination Wave 1.2/50 $\mu$ s Open Circuit Voltage 8/20 $\mu$ s Short Circuit Current
<b>Test Voltage:</b>	AC Power Port ~ line to line: 1kV, line to earth: 2kV DC Power Port ~ line to line and line to earth: 0.5kV Signal/Control Port ~ line to earth: 1kV
<b>Surge Input/Output:</b>	AC Power Line: L-N / L-PE / N-PE DC Power Line: L-N / L-PE / N-PE Signal Line: L-G
<b>Generator Source Impedance:</b>	2 ohm between networks 12 ohm between network and ground 42 ohm between network and ground
<b>Polarity:</b>	Positive/Negative
<b>Phase Angle:</b>	AC Power: 0° / 90° / 180° / 270° DC Power: 0°
<b>Pulse Repetition Rate:</b>	1 time / min. (maximum)
<b>Number of Tests:</b>	5 positive and 5 negative at selected points

### 8.6.2. TEST INSTRUMENT

Immunity Shield Room				
Name of Equipment	Manufacturer	Model	Serial Number	Calibration Due
CDN	EMC-Partner	CDN-UTP8	1505	02/06/2019
EMC Immunity Tester	EMC Partner	TRANSINT 2000	1117	03/13/2019
Software	Genecs Ver. 3.27			

**NOTE:** 1. The calibration interval of the above test instruments is 12 months and the calibrations are traceable to NML/ROC and NIST/USA.  
2. N.C.R.= No Calibration required.

**8.6.3. TEST PROCEDURE** (please refer to measurement standard or CCS SOP PA-025)

## a) For EUT power supply:


The surge is applied to the EUT power supply terminals via the capacitive coupling network. Decoupling networks are required in order to avoid possible adverse effects on equipment not under test that may be powered by the same lines, and to provide sufficient decoupling impedance to the surge wave. The power cord between the EUT and the coupling/decoupling networks was shorter than 2 meters in length.

## b) For test applied to unshielded un-symmetrically operated interconnection lines of EUT:

The surge was applied to the lines via the capacitive coupling. The coupling / decoupling networks didn't influence the specified functional conditions of the EUT. The interconnection line between the EUT and the coupling/decoupling networks was shorter than 2 meters in length.

## c) For test applied to unshielded symmetrically operated interconnection / telecommunication lines of EUT:

The surge was applied to the lines via gas arrestors coupling. Test levels below the ignition point of the coupling arrestor were not specified. The interconnection line between the EUT and the coupling/decoupling networks was shorter than 2 meters in length.

**8.6.4. TEST SETUP**

- For the actual test configuration, please refer to the related item – Photographs of the Test Configuration.



### 8.6.5. TEST RESULTS

#### AC Power

Temperature	19°C	Humidity	57% RH
Pressure	1010mbar	Tested By	Kevin Chang
Required Passing Performance		Criterion B	

Test Point	Polarity	Test Level (kV)	Performance Criterion	Observation	Result
L - N	+/-	1	<input checked="" type="checkbox"/> A <input type="checkbox"/> B	Note <input checked="" type="checkbox"/> 1 <input type="checkbox"/> 2	PASS
L - PE	+/-	2	<input checked="" type="checkbox"/> A <input type="checkbox"/> B	Note <input checked="" type="checkbox"/> 1 <input type="checkbox"/> 2	PASS
N - PE	+/-	2	<input checked="" type="checkbox"/> A <input type="checkbox"/> B	Note <input checked="" type="checkbox"/> 1 <input type="checkbox"/> 2	PASS
RJ45	+/-	1	<input checked="" type="checkbox"/> A <input type="checkbox"/> B	Note <input checked="" type="checkbox"/> 1 <input type="checkbox"/> 2	PASS
COM 1 / COM 3	+/-	1	<input checked="" type="checkbox"/> A <input type="checkbox"/> B	Note <input checked="" type="checkbox"/> 1 <input type="checkbox"/> 2	PASS
COM 2	+/-	1	<input checked="" type="checkbox"/> A <input type="checkbox"/> B	Note <input checked="" type="checkbox"/> 1 <input type="checkbox"/> 2	PASS

**NOTE:** 1. There was no change compared with initial operation during the test.

#### DC Power

Temperature	19°C	Humidity	57% RH
Pressure	1010mbar	Tested By	Kevin Chang
Required Passing Performance		Criterion B	

Test Point	Polarity	Test Level (kV)	Performance Criterion	Observation	Result
L - N	+/-	0.5	<input checked="" type="checkbox"/> A <input type="checkbox"/> B	Note <input checked="" type="checkbox"/> 1 <input type="checkbox"/> 2	PASS
L - PE	+/-	0.5	<input checked="" type="checkbox"/> A <input type="checkbox"/> B	Note <input checked="" type="checkbox"/> 1 <input type="checkbox"/> 2	PASS
N - PE	+/-	0.5	<input checked="" type="checkbox"/> A <input type="checkbox"/> B	Note <input checked="" type="checkbox"/> 1 <input type="checkbox"/> 2	PASS
RJ45	+/-	1	<input checked="" type="checkbox"/> A <input type="checkbox"/> B	Note <input checked="" type="checkbox"/> 1 <input type="checkbox"/> 2	PASS
COM 1 / COM 3	+/-	1	<input checked="" type="checkbox"/> A <input type="checkbox"/> B	Note <input checked="" type="checkbox"/> 1 <input type="checkbox"/> 2	PASS
COM 2	+/-	1	<input checked="" type="checkbox"/> A <input type="checkbox"/> B	Note <input checked="" type="checkbox"/> 1 <input type="checkbox"/> 2	PASS

**NOTE:** 1. There was no change compared with initial operation during the test.

## 8.7. CONDUCTED RADIO FREQUENCY DISTURBANCES (CS)

### 8.7.1. TEST SPECIFICATION

**Basic Standard:** IEC 61000-4-6

**Frequency Range:** 0.15 MHz ~ 80 MHz

**Field Strength:** 10 Vrms

**Modulation:** 1kHz Sine Wave, 80%, AM Modulation

**Frequency Step:** 1 % of preceding frequency value

**Coupled cable:** AC / DC Power Mains, Unshielded; RJ45 Line, Unshielded;  
COM Line, Shielded

**Coupling device:** CDN-M3/M2 (3/2 wires); EM-Clamp

### 8.7.2. TEST INSTRUMENT

CS Room				
Name of Equipment	Manufacturer	Model	Serial Number	Calibration Due
CDN	SCHAFFNER	CDN M225	16500	12/03/2019
CDN	TESEQ	CDN S751A	37469	06/19/2019
CDN	Teseq	CDN M016	35821	02/12/2019
CDN	FCC	FCC-801-M3-25A	9973	02/12/2019
EM Clamp	SCHAFFNER	KEMZ 801	19239	02/06/2019
Immunity Test System	TESEQ	NSG 4070	39581	12/04/2019
Software	NSG 4070 Control Program V1.2.0			

**NOTE:** 1. The calibration interval of the above test instruments is 12 months and the calibrations are traceable to NML/ROC and NIST/USA.  
2. N.C.R.= No Calibration required.

### 8.7.3. TEST PROCEDURE (please refer to measurement standard or CCS SOP PA-026)

The EUT shall be tested within its intended operating and climatic conditions.


The test shall be performed with the test generator connected to each of the coupling and decoupling devices in turn, while the other non-excited RF input ports of the coupling devices are terminated by a 50-ohm load resistor.

The frequency range was swept from 150 kHz to 80 MHz, using the signal level established during the setting process and with a disturbance signal of 80 % amplitude. The signal was modulated with a 1 kHz sine wave, pausing to adjust the RF signal level or the switch coupling devices as necessary. The sweep rate was  $1.5 \times 10^{-3}$  decades/s. Where the frequency range is swept incrementally, the step size was 1 % of preceding frequency value from 150 kHz to 80 MHz.

The dwell time at each frequency was less than the time necessary for the EUT to be exercised, and able to respond. Sensitive frequencies such as clock frequency(ies) and harmonics or frequencies of dominant interest, was analyzed separately.

Attempts were made to fully exercise the EUT during testing, and to fully interrogate all exercise modes selected for susceptibility.

### 8.7.4. TEST SETUP



**Note:** 1. The CDNs and / or EM clamp used for real test depends on ports and cables configuration of EUT.  
2. The EUT clearance from any metallic obstacles shall be at least 0.5m

- For the actual test configuration, please refer to the related item – Photographs of the Test Configuration.

#### NOTE:

##### TABLE-TOP AND FLOOR-STANDING EQUIPMENT

The equipment to be tested is placed on an insulating support of 0.1 meters height above a ground reference plane. All relevant cables shall be provided with the appropriate coupling and decoupling devices at a distance between 0.1 meters and 0.3 meters from the projected geometry of the EUT on the ground reference plane.

## 8.7.5. TEST RESULTS

## AC Power

Temperature	20°C	Humidity	58% RH
Pressure	1009mbar	Tested By	Stanley Cheng
Required Passing Performance		Criterion A	

Frequency Band (MHz)	Field Strength (Vrms)	Cable	Injection Method	Performance Criterion	Observation	Result
0.15 ~ 80	10	AC Power Line (0.3m)	CDN-M3	<input checked="" type="checkbox"/> A <input type="checkbox"/> B	Note <input checked="" type="checkbox"/> 1 <input type="checkbox"/> 2	PASS
0.15 ~ 80	10	RJ45 Line (0.3m)	EM-Clamp	<input checked="" type="checkbox"/> A <input type="checkbox"/> B	Note <input checked="" type="checkbox"/> 1 <input type="checkbox"/> 2	PASS
0.15 ~ 80	10	COM 1 / COM 3 Line (3.0m)	EM-Clamp	<input checked="" type="checkbox"/> A <input type="checkbox"/> B	Note <input checked="" type="checkbox"/> 1 <input type="checkbox"/> 2	PASS
0.15 ~ 80	10	COM 2 Line (3.0m)	EM-Clamp	<input checked="" type="checkbox"/> A <input type="checkbox"/> B	Note <input checked="" type="checkbox"/> 1 <input type="checkbox"/> 2	PASS

**NOTE:** 1. There was no change compared with initial operation during the test.

## DC Power

Temperature	19°C	Humidity	42% RH
Pressure	997mbar	Tested By	Lion Lee
Required Passing Performance		Criterion A	

Frequency Band (MHz)	Field Strength (Vrms)	Cable	Injection Method	Performance Criterion	Observation	Result
0.15 ~ 80	10	DC Power Line (0.3m)	CDN-M2	<input checked="" type="checkbox"/> A <input type="checkbox"/> B	Note <input checked="" type="checkbox"/> 1 <input type="checkbox"/> 2	PASS
0.15 ~ 80	10	RJ45 Line (0.3m)	EM-Clamp	<input checked="" type="checkbox"/> A <input type="checkbox"/> B	Note <input checked="" type="checkbox"/> 1 <input type="checkbox"/> 2	PASS
0.15 ~ 80	10	COM 1 / COM 3 Line (3.0m)	EM-Clamp	<input checked="" type="checkbox"/> A <input type="checkbox"/> B	Note <input checked="" type="checkbox"/> 1 <input type="checkbox"/> 2	PASS
0.15 ~ 80	10	COM 2 Line (3.0m)	EM-Clamp	<input checked="" type="checkbox"/> A <input type="checkbox"/> B	Note <input checked="" type="checkbox"/> 1 <input type="checkbox"/> 2	PASS

**NOTE:** 1. There was no change compared with initial operation during the test.

## 8.8. POWER FREQUENCY MAGNETIC FIELD

### 8.8.1. TEST SPECIFICATION

**Basic Standard:** IEC 61000-4-8

**Frequency Range:** 50Hz/60Hz

**Field Strength:** 30 A/m

**Observation Time:** 1 minute

**Inductance Coil:** Rectangular type, 1mx1m

### 8.8.2. TEST INSTRUMENT

Immunity Shield Room				
Name of Equipment	Manufacturer	Model	Serial Number	Calibration Due
AC/DC Clamp Meter	Fluke	353	33360025	07/03/2019
Magnetic Field Coil	Teseq	INA 703 W/ 2141	1976 / 1413	04/08/2019
Magnetic Field Meter	Sypris	4080	0247	11/01/2019
5kVA Power Source	Teseq	5001IX-208-TSQ	1207A03643	04/08/2019
Software	Win2120Ver. 5.0			


**NOTE:** 1. The calibration interval of the above test instruments is 12 months and the calibrations are traceable to NML/ROC and NIST/USA.

2. N.C.R.= No Calibration required.

### 8.8.3. TEST PROCEDURE (please refer to measurement standard or CCS SOP PA-027)

- The equipment is configured and connected to satisfy its functional requirements. It shall be placed on the GRP with the interposition of a 0.1m-thick insulating support.
- The equipment cabinets shall be connected to the safety earth directly on the GRP via the earth terminal of the EUT.
- The power supply, input and output circuits shall be connected to the sources of power supply, control and signal.
- The cables supplied or recommended by the equipment manufacturer shall be used. 1 meter of all cables used shall be exposed to the magnetic field.

#### 8.8.4. TEST SETUP



- For the actual test configuration, please refer to the related item – Photographs of the Test Configuration.

**NOTE:****TABLETOP EQUIPMENT**

The equipment shall be subjected to the test magnetic field by using the induction coil of standard dimension (1 m x 1 m). The induction coil shall then be rotated by 90 degrees in order to expose the EUT to the test field with different orientations.

**FLOOR-STANDING EQUIPMENT**

The equipment shall be subjected to the test magnetic field by using induction coils of suitable dimensions. The test shall be repeated by moving and shifting the induction coils, in order to test the whole volume of the EUT for each orthogonal direction. The test shall be repeated with the coil shifted to different positions along the side of the EUT, in steps corresponding to 50 % of the shortest side of the coil. The induction coil shall then be rotated by 90 degrees in order to expose the EUT to the test field with different orientations.

### 8.8.5. TEST RESULTS

#### AC Power

<b>Temperature</b>	20°C	<b>Humidity</b>	57% RH
<b>Pressure</b>	1010mbar	<b>Tested By</b>	Stanley Cheng
<b>Required Passing Performance</b>		<b>Criterion A</b>	

Direction	Field Strength (A/m)	Performance Criterion	Observation	Results
X	30	A	Note	PASS
Y	30	A	Note	PASS
Z	30	A	Note	PASS

**NOTE:** There was no change compared with initial operation during the test.

#### DC Power

<b>Temperature</b>	20°C	<b>Humidity</b>	57% RH
<b>Pressure</b>	1010mbar	<b>Tested By</b>	Stanley Cheng
<b>Required Passing Performance</b>		<b>Criterion A</b>	

DIRECTION	Field Strength (A/m)	Performance Criterion	OBSERVATION	RESULTS
X	30	A	Note	PASS
Y	30	A	Note	PASS
Z	30	A	Note	PASS

**NOTE:** There was no change compared with initial operation during the test.

## 8.9. VOLTAGE DIPS & VOLTAGE INTERRUPTIONS

### 8.9.1. TEST SPECIFICATION

**Basic Standard:** IEC 61000-4-11

**Test duration time:** Minimum three test events in sequence

**Interval between event:** Minimum 10 seconds

**Phase Angle:** 0° / 180°

**Test cycle:** 3 times

### 8.9.2. TEST INSTRUMENT


Immunity shielded room				
Name of Equipment	Manufacturer	Model	Serial Number	Calibration Due
AC/DC Clamp Meter	Lutron	CM-9930R	I.200121	05/21/2019
EMC Immunity Tester	EMC Partner	TRANSINT 2000	1117	03/13/2019
Software	Genecs Ver. 3.27			

**NOTE:** 1. The calibration interval of the above test instruments is 12 months and the calibrations are traceable to NML/ROC and NIST/USA.  
2. N.C.R.= No Calibration required.

### 8.9.3. TEST PROCEDURE (please refer to measurement standard or CCS SOP PA-028)

1. The EUT and support units were located on a wooden table, 0.8 m away from ground floor.
2. Setting the parameter of tests and then perform the test software of test simulator.
3. Conditions changes to occur at 0 degree crossover point of the voltage waveform.
4. Recording the test result in test record form.

### 8.9.4. TEST SETUP



- For the actual test configuration, please refer to the related item – Photographs of the Test Configuration.



### 8.9.5. TEST RESULTS

Temperature	19°C	Humidity	57% RH
Pressure	1010mbar	Tested By	Kevin Chang
Required Passing Performance	<b>Criterion B: 0% residual 1 cycle</b> <b>Criterion C: i) 40% residual 10/12 cycles at 50/60Hz</b> <b>ii) 70% residual 25/30 cycles at 50/60Hz</b> <b>iii) 0% residual for 250/300 cycles at 50/60Hz</b>		

Test Power: 230Vac, 50Hz				
Voltage (% Residual)	Duration (Cycle)	Performance Criterion	Observation	Test Result
0	1	<input checked="" type="checkbox"/> A <input type="checkbox"/> B <input type="checkbox"/> C	Note <input checked="" type="checkbox"/> 1 <input type="checkbox"/> 2	PASS
40	10	<input checked="" type="checkbox"/> A <input type="checkbox"/> B <input type="checkbox"/> C	Note <input checked="" type="checkbox"/> 1 <input type="checkbox"/> 2	PASS
70	25	<input checked="" type="checkbox"/> A <input type="checkbox"/> B <input type="checkbox"/> C	Note <input checked="" type="checkbox"/> 1 <input type="checkbox"/> 2	PASS
0	250	<input type="checkbox"/> A <input type="checkbox"/> B <input checked="" type="checkbox"/> C	Note <input type="checkbox"/> 1 <input checked="" type="checkbox"/> 2	PASS

Test Power: 230Vac, 60Hz				
Voltage (% Residual)	Duration (Cycle)	Performance Criterion	Observation	Test Result
40	12	<input checked="" type="checkbox"/> A <input type="checkbox"/> B <input type="checkbox"/> C	Note <input checked="" type="checkbox"/> 1 <input type="checkbox"/> 2	PASS
70	30	<input checked="" type="checkbox"/> A <input type="checkbox"/> B <input type="checkbox"/> C	Note <input checked="" type="checkbox"/> 1 <input type="checkbox"/> 2	PASS
0	300	<input type="checkbox"/> A <input type="checkbox"/> B <input checked="" type="checkbox"/> C	Note <input type="checkbox"/> 1 <input checked="" type="checkbox"/> 2	PASS

**NOTE:** 1. There was no change compared with initial operation during and after the test. No unintentional response was found during the test.

2. EUT shut down, it could not become normal except reinstalled by operator.

## 9 PHOTOGRAPHS OF THE TEST CONFIGURATION

### CONDUCTED EMISSION TEST

#### AC Power



## DC Power




**CONDUCTED EMISSION TEST AT TELECOMMUNICATION PORTS****RJ45 Telecom Port with ISN (10Mbps & 100Mbps)**




## RADIATED EMISSION TEST

### Below 1GHz



**Above 1GHz**

**966 CHAMBER TEST**




### Harmonic & Flick Test (AC Power)




### ESD Test (AC Power)





**ESD Test (DC Power)****RS Test (AC Power)**

**RS Test (DC Power)****EFT Test (AC Power)**

**EFT Test (DC Power)****EFT For I/O Test (RJ45 / AC Power)**



**EFT For I/O Test (COM 1 / COM 3 / AC Power)****EFT For I/O Test (COM 2 / AC Power)**

## EFT For I/O Test (RJ45 / DC Power)



## EFT For I/O Test (COM 1 / COM 3 / DC Power)




**EFT For I/O Test (COM 2 / DC Power)****Surge Test (AC Power)**



### Surge Test (DC Power)




### Surge For I/O Test (RJ45 / AC Power)



**Surge For I/O Test (COM 1 / COM 3 / AC Power)****Surge For I/O Test (COM 2 / AC Power)**



**Surge For I/O Test (RJ45 / DC Power)****Surge For I/O Test (COM 1 / COM 3 / DC Power)**

## Surge For I/O Test (COM 2 / DC Power)



## CS Test (AC Power)



## CS Test (DC Power)



## CS For I/O Test (RJ45 / AC Power)





## CS For I/O Test (COM 1 / COM 3 / AC Power)



## CS For I/O Test (COM 2 / AC Power)



## CS For I/O Test (RJ45 / DC Power)



## CS For I/O Test (COM 1 / COM 3 / DC Power)



### CS For I/O Test (COM 2 / DC Power)



### PFMF Test (AC Power)



**PFMF Test (DC Power)****Voltage Dips / Interruptions Test (AC Power)**